

**Roads & Building Department
Government of Gujarat**

Executive Engineer,
Baroda Electrical Division, Baroda.

**TENDER
FOR
ELECTRICAL WORK**

Name of Work:

**Package: Construction of New Animal
Husbandary Epic Center at (1)
Sarsavani (2) Latipura and (3) Mujpur,
Ta. Padra, Dist. Vadodara (Deposit
Work)**

Item No. 92 to 126

Estimated Cost Rs. _____

Date of Issue of Tender _____

Last Date of Receiving Tender _____

Name of Work :-

INDEX

	Tender document contain Pages 1 to 55	Page No
A	Addendum	
B	Memorandum	1-A
C	Instructions to tenderers	1
D	Forms of tender for electrical work (induplicate) with schedule of time limit	2
E	General Conditions	4
F	Data Sheet for E-tendering	7
G	General Conditions of contract for electrical works	9
H	Schedule-A	
I	Schedule-B	
J	Specification for electrical works	22
K	List Of Approved Electrical Products (Separate sheet attached)	50 to 55
L	Amount put to tender Rs.	
M	Tender Fee Rs.	
N	Earnest Money Rs.	
O	Security Deposit Rs. Performance Bond Rs.	

Last Date of Receipt of Tenders by R.P.A.D. Dt. / /

OR

* Downloading of tender documents	From date / /
Start & End Date	Up to date / / Till ; Hrs.

Issued to M/s. _____

Divisional Accountant / D.A.O.
Executive Engineer.

- (Only in case of Tender above Rupees Ten Lacs)

GENERAL CONDITIONS OF CONTRACT

1. Definition of terms :

In construing these general conditions and the annexed specification the following words shall have the meaning here assigned to them unless there is something in the subject or context inconsistent with such constructions

The "GOVERNOR OF GUJARAT" shall include his successors and assigns.

The "Engineer" shall mean the Ex. Engineer, Electrical Division, for the time being attached to the Public Works Department of the Gujarat State or such other officer as may be appointed by the Ex. Engineer. Electrical Division to supervise the work on behalf of the Governor of Gujarat.

The "CONTRACTOR" shall mean the Tenderer whose tender, shall be accepted by the Governor of Gujarat. And shall include the tenderer's legal personal representatives or successors and assigns.

"PLANT" shall mean and include any machine, fixed or movable, used for the generation or transmission of power or actuated by power.

"WORK" or "WORKS" shall mean the whole of the plant and material to be provided and work to be done, executed or carried out by the contractor under the contract.

The "CONTRACT" shall mean all the documents by which the agreement by the contractor to be provided to execute or carry out the plant work or works shall be constituted or in or by which the terms of such agreement or any of them are contained or set forth specially as per these General conditions, any special conditions attached to or issued with these conditions, the specification, the Drawing tile invitation for Tenders (if any) or any other letter, notice or document upon or with reference to which the Tender is made and the schedule of prices (if any) furnished by the contractor with his Tender.

The "SPECIFICATION" shall mean the specification annexed to these General conditions and the Schedule thereto (if any).

The "SITE" shall mean the whole of the premises, buildings and grounds in or upon which the Plant "York or works is or are to be provided, executed, erected, done or carried out.

The "DRAWINGS" shall mean the drawings issued with the specification which will ordinarily be identified by being signed by the Engineer and any further drawings submitted by the contractor with his tender and duly signed by him and accepted or approved by the. Engineer and all other drawings supplied or furnished by the contractor or by the Engineer in accordance with these General conditions.

The "SCHEDULE" shall mean the schedule or schedules attached to the specification.

2. Contractor to inform himself fully:

The contractor shall be deemed to have carefully examined the invitation for Tender (if any) the general and any special conditions, the specification and Drawings and the Schedule of price (if any). In case of discordance or want of agreement between or amongst the several things herein described as the grounds or data of the contract, then these conditions shall have precedence of and be held to be more correct and binding and in like manner detailed drawings shall be held to be more correct, and binding than general drawings and in like manner drawing made to a large scale, or for special instruction, shall be held to be more correct and binding than drawing made to a smaller scale, or for general instruction and figured dimensions shall be held to be more correct than dimensions by scale but subject nevertheless in case of doubt or dispute as to any of the matters aforesaid to the determination and decision of Engineer as hereafter is more particularly mentioned and provided always that nothing herein contained shall limit the powers of the Engineer hereinafter mentioned.

3. Security Deposit:

The person/persons whose tender is accepted (hereinafter called the "Contractor" which expression shall, unless excluded by, or repugnant to the context include his Legal heirs, executors, administrators and assignees shall (a) Deposit with the Executive Engineer a sum sufficient to make up the full security deposit specified in the tender in cash or Government securities (as mentioned in para 208 of Gujarat Public Works Department Manual Vol. 1) duly transferred in the name of the Executive Engineer or fixed deposit receipts or Term Deposits of Narmada Project in the name of the Executive Engineer within a period of 10 days from the date of receipt of the Notification of acceptance of his tender. or (b) (i) deposit fifty percentage of the total security deposits as specified in the tender form with the Executive Engineer in form of small saving schemes or securities of Sardar Sarovar Narmada Nigam or F.D. Rs. of scheduled bank. However, the Contractor can deposit twenty five percentage of total security deposit in the form of Govt. security (as mentioned in para 208 of Gujarat Public Works Department Manual Vol. 1) or Term Deposit of Narmada Project duly transferred in the name of the Executive Engineer, or fixed deposit receipts in the name of the

Executive Engineer within a period of ten days from the date of receipt of notification of acceptance of his tender. If the security deposit is not paid within the above specified time, no work order will be issued, till the issue about delay is

finally decided by the competent authority. (b) (ii) The Government shall be deemed to have been authorised to deduct the balance of fifty percentage of the security deposit as specified in the tender form from the amounts that become payable to the contractor for the work done under the contract from time to time, such deduction shall not exceed ten percentage of the amount so payable and the whole amount paid in cash or by way of deduction shall be held by Government by way of security deposit. For the works whose estimated amount is more than rupees fifteen lacs, the Contractor shall have to give the performance bond supported by F. D. R or Unconditional, So that same can be encashed without giving any reason by the Executive Engineer Non Transferable and Irrevocable Bank Guarantee of any schedule bank equivalent to five percentage of the estimated amount put to tender along with the initial security deposits. All compensation, Liquidated damages or other sums or money payable by the contractor to Government under the terms of this contract shall be deducted from or recouped by the realisation of a sufficient part of his security deposit, or from the interest arising there from or performance bond or from any sums which may be due or may become due by Government to the Contractor on any account whatsoever and whether in respect of this contract, any other contract, or otherwise. In the event of his security deposit being reduced by reason of any such deduction or recoupment as aforesaid, the contractor shall within ten days thereafter, make good in cash or in Government securities transferred as aforesaid any sum or sums required to make good the shortfall in the amount of the security deposit. The security deposit, when paid as above shall at the cost of the depositor, be converted into interest bearing Government securities in the name of Executive Engineer provided that the depositor has expressly desired this in writing. This is subject to the condition that twenty five percentage of the total security deposit must be held in the form of small saving Schemes or Term Deposits of Narmada Project. If the full amount of the security deposit to be paid as above within the period specified above, is not paid the tender/contract already accepted shall be considered as cancelled and legal steps shall be taken against the contractor for recovery of the amounts.

Special condition

As there is replacement warranty has to provide for LED fitting for 3 years, so security Deposit an amount (1) **Rs.2447/-** + (2) **Rs. 2447/-** + (3) **Rs. 2447/-** will be released only after completion of warranty period or the replacement of defective LED fitting whichever is later. Further after issuing the notice to the contractor for replacement of defective material, he has to take up the work of replacement within 10 days from the date of issuing the said notice, in case where the delay for replacement, the contractor shall be penalized by Rs. 100/- per day for such delay. In case of non replacement of the defective material action will be taken against the contractor to keep his registration in abeyance for three years and his full security deposit will be forfeited to the Government.

Annexure PERFORMANCE BOND

(The date of this bond must not be prior to the date of the instrument in connection with which it is given)

.....
Principal (Contractor)

.....
Surety (Bank)

.....
Sum of bond (express in words and figures)

.....
Contract No. and date of contract

NOW ALL MEN BY THESE PRESENTS, THAT WE, THE PRINCIPALS AND SURETY above named are held and firmly bound unto the.....hereinafter called the Employer in the amount stated for payment of which sum, well and truly to be made, we bind ourselves, our heirs, executors, administrators and successors jointly and severally, firmly by these presents subject to the provisions of which the aforesaid Contractor on demand and without demand on a claim being 'made by the Employer.

THE CONDITION OF THIS OBLIGATION IS SUCH, that whereas the principals have entered in to a contract with the Employer numbered and dates as shown above and hereto attached for the execution of work.....

NOW THEREFORE, if the Principal shall well and truly perform and fulfill all the undertakings, covenants, terms, conditions and agreements of said contract during the original terms of the said Contract and any extensions thereof that may be granted by the Employer with, or without notice to the surety and during the life or any guarantee required under the contract, and shall also well and truly perform and fulfill all the Undertakings, covenants, terms, conditions and agreements of any all duty and unduly authorized modifications of said Contract that may hereafter be made, notice of which modifications to the surety being hereby waived or shall pay over, make good and reimburse to the Employer all loss and damages which the employer may sustain by reason of failure or default on the part of said Principal so to do.

We..... further agree that the guarantee herein Contained shall remain in full force and effect during the period that would be taken for the validity of the

said Contract, and that it shall continue to be enforceable till all the dues of the employer under or by'. virtue of the Contract have been fully paid and its claims satisfied or discharged or till the Employer certifies that the terms and conditions of the Contract have been fully and properly carried out by the said Contractor and accordingly discharges the guarantee. Unless a demand or claim under this guarantee is made on us in writing on or before the we shall be discharged from all liability under this guarantee thereafter.

IN WITNESS WHERE OF, the above bounded parties have executed this instrument under their several seals on the date indicated above the name and corporate seal of each corporate party being hereto affixed and these presents duly signed by its undersigned representatives, pursuant to authority of its governing body.

In the presence of witness

Individual

Principal

1..... as to (seal)
2..... as to (seal)
3..... as to (seal)
4..... as to (seal)

Attested

by.....affix Corporate Seal

Corporate Surety

Business address

Affix by..... corporate Seal

Title

For and on behalf of the Employer

4, Mistake in contractor's Drawings:

The contractor shall submit such drawings as may be required and shall be responsible for any discrepancies. errors or omissions in any drawings or other particulars supplied by him notwithstanding that such drawings or particulars may have been approved by Engineer.

5. Patent Rights etc.

The contractor shall fully indemnify the Governor of Gujarat against all actions suits claims demands, costs, charges and expenses arising from or incurred by reason of any infringement or alleged infringement, of any, letters patent, design. trademark or name copyright or other protected rights in respect of any machine, plant, work materials thing or system or method of using, fixing, working or arrangement used or fixed or supplied by the contractor but this indemnity shall not extend or apply to any action. suit, claim, demand, cost charges or expenses arising from or incurred by reason of the use of the work or any part thereof otherwise than in the manner of for a purpose' contemplated by the contract. All royalties and other similar payments which may have to be paid for the use of any machine, plant. work, material, thing, system or method as aforesaid (whether payable in one sum or by installments or otherwise) shall be covered by the contract price and payable by the contractor.

In the event of any claim or demand being made or action or suit brought against the Governor of Gujarat in respect of any such matter or matters as all negotiations for the settlement of such claim or demand and such action aforesaid the contractor shall be duly notified, thereof, and he shall conduct or suit also be conducted by him subject if and so far as the Governor of Gujarat shall think proper under the Supervision & Control of Governor of Gujarat through the officer duly authorised on his behalf.

6. Excess over Tender quantities, Extra items & Variations in Specifications, Drawings etc.:

6.1 The Engineer-in-charge shall have power to make any alterations additions in or to the original specifications. drawings,- designs and instructions that may appear to him to be necessary or advisable during the progress of the work and the contractor shall be bound to carry out the work in accordance with any instructions in this connection which may be given to him in writing signed by the Engineer-in-charge and such alternation shall not invalidate the contract and additional work which the contractor may be directed to do in the manner above specified as part of the work shall be carried out by the contractor on the manner above specified as part of the work shall be carried out by the contractor in the same conditions in all respects on which he agreed to do the work and at the same rate as are specified in the tender for the main work.

6.2 Except that when the quantity of any item exceeds the quantity as in the tender by more than 10% the contractor will be paid for the quantity in excess of 10% at the rate entered in the S.O.R. of the year during which the excess in quantity is first executed and for the materials consumed in excess quantity the rate for the materials to be charged would be the basic rate taken into. account for fixing the rate for the S. O. R. above instead of the rate stipulated in schedule-A.

6.3 If the additional or altered work includes any class of work for which no rate is specified in this contract, then such class of work shall be carried out.

(i) At the rate derived from the item within the contract which is comparable to the one involving additional or altered class of work; where there are more than one comparable items; the item of the contract which is nearest in comparison with regard to class or classes of the work involved shall be selected and the decision of the Superintending Engineer as to the nearest comparable item shall be final and binding on the contractor;

(ii) If the rate cannot be derived in accordance with (i) above, such class of works shall be carried out at the rate entered in the Schedule of Rates of the Division for the year in which, the tender was received, increased or decreased by the percentage by which the tender received, increased or decreased by the percentage by which the tender amount is more or less as compared or decreased by the percentage by which the tender amount is more or less as compared to the amount arrived at the rates in the "Schedule of Rates" of the Division in the year in which the tender was received. If the Schedule of rates calculated considering such items which were included in the "Schedule of Rates" of the Division for the year and for materials consumed on such item the rate to be charged would be the basic rate taken into account for fixing the rate in S.O.R. referred to above, instead of the rate.

(iii) If it is not possible to arrive at the rate from (1) and (ii) above, such class of work shall be carried out at the rate decided by; the competent authorities on the basis of detailed rate analysis after hearing the contractor before a committee of two superintending Engineers stationed at the same place or the nearest place.

6.4 If the additional or altered work, for which no rate is entered in the "Schedule or Rates" of the Division is ordered to be carried out before the rate is agreed upon, then the contractor shall within seven days of the date of receipt by him of the order to carry out the work, inform the Engineer-in-charge of the rate, which it is his intention to charge for such class of work and if the Engineer-in-charge does not agree to this rates, he shall by notice in writing be at liberty to cancel his order to carry out such class of work and arrange to carry it out in such manner as he may consider it advisable, provided always that if the contractor 5' 111 commence work or incur any expenditure in regard thereof before the rates shall have been determined as lastly herein before mentioned, then in such cases he shall only be entitled to be paid in respect of the work carried out or expenditure incurred by him prior to the date of the determination of the -rate as aforesaid according to such rate or rates as shall be fixed by the Engineer-in-charge, In the event of the dispute, the decision of the Superintending Engineer of the Circle shall be final.

Where, however, the work is to be executed according to the designs, drawings and specifications recommended by the contractor and accepted by the competent authority, the alternation above referred to shall be within the scope of such designs, drawings and specifications appended to the tenders.

The time limit for the completion of the work shall be extended in the proportion that the increase in the cost occasioned by alternations bears to the cost of the original contract work and the certificate of the Engineer-in-charge as to such proportion shall final and conclusive.

7. Workmanship and Materials:

The work shall be carried out in all respects with workmanship and materials of the best and most substantial and approved qualities to the entire satisfaction of the Engineer who may reject any plant, apparatus of material or workmanship which shall in his opinion be of defective quality any such rejection to be final and conclusive. The contractor shall at his own expenses provide all material labour, haulage, power, tools, tackles and apparatus necessary to execute and complete the works and plant in the manner aforesaid.

8. Use of work pending completion:

The Governor of Gujarat shall be at liberty at any time to put into beneficial use the whole or any part of the work he may desire to use pending the formal completion and taking over of the same.

9. Subletting of contract:

The contractor shall not without the consent in writing of the Governor of Gujarat under the hand of the Engineer assign or sublet the contract nor make any sub contract with any person or persons for the execution of any portion of the work other than for raw materials, pr for any part of the work of which the manufacturers are named on his contract.

10. Protection and liability for accidents, Theft and Damage.

The Contractor shall at all items until the commencement of the period maintenance as provided in clause 16 property and sufficiently cover up and protect all materials delivered on site from damage or injury by exposure to the weather and shall take every proper precaution against accident, damage or injury on the same from any cause, The contractor shall be and remain answerable and liable for all accident and damage thereto which until the commencement of the period of maintenance as provided for under clause 16 may arise or be occasioned but the acts or omissions of the contractor or his workmen, agents. servants or sub-contractors and all losses and damages arising from such accidents, damage or injuries as aforesaid shall be made good in the most complete and substantial manner by al)d at sole cost of .the contractor and to the satisfaction of the Engineer.

Provided that should the Engineer certify, that the work has been completed but that owing to circumstances over which the contractor has no control the work cannot be taken over the contractor shall not be held liable for any loss of or damage to the work occasioned by such delay in taking over and occurring more than one month after date of completion of the work as certified by the Engineer.

Until the work shall be or deemed to be taken over as hereafter provided the Contractor shall also indemnify to Governor of Gujarat from and against all claims and demands, suits. proceedings, cost and expenses in

respect in respect of or in connection with any injury to person or damage to property by whomsoever sustained or by defective design work or materials made, done, furnished or supplied by the contractor. The Contractor shall also be responsible for thefts of any property of the Governor of Gujarat or of others committed by any employees of his own or his subcontractors and shall be liable for the costs of replacing any property stolen.

11. Insurance :

Subject as hereinafter provided the contractor shall at his own expense insure and at all times prior to the commencement of the period of maintenance keep insured against destruction or damage by fire or earthquake storm and tempest such plant and materials ordered for the work as may for the time being be upon the site for the full value of such plant and materials.

12. Materials brought on the site:

All materials, tools and tackle brought to and delivered upon the site for the purpose of the work shall from the time of their being so brought vest in and be the property of the Governor of Gujarat but maybe used for the purpose of the work but for that purpose only and not on any account be removed or taken away by the contractor or any other person without the express permission in writing of the Engineer, but the Contractor shall nevertheless (Subject as hereinafter provided be solely liable and responsible for any loss or destruction thereof or damage unless resulting from causes beyond the Contractor's control not being causes insurance against destruction or damage from which is provided for in clause 11. The Governor of Gujarat shall have a lien on such materials, tools and tackle for any sum which may to any time prior to the completion of the works be due or owing to him by the Contractor under in respect of or by reason of the Contract and shall be at liberty to sell and dispose of any of such materials, tools and tackle remaining after the completion of the works in such manner as he shall think fit, and to apply the proceeds in or towards the satisfaction of such sum or sums so due or owing as aforesaid but subject to such lien and power of sale and disposal such surplus materials, tools and tackle shall belong to the contractor and may be removed and disposed of by him as he shall think fit after the lien is withdrawn by the Engineer in charge.

13. Default:

If the Contractor shall at any time fail in the opinion of the Engineer to proceed with, the work with due diligence and expedition, or shall refuse, neglect or omit to comply with any orders given to him in writing by the Engineer in accordance with the provisions of these conditions or shall commit any other breach of the provision of the contract, the Engineer shall be at liberty to give notice in writing to the Contractor to make good the failure neglect, omission or breach complained of and should the Contractor shall fail to comply with any such notice within such period as may be prescribed in such period as may be prescribed in such' notice then and in such case the Governor of Gujarat shall be at liberty to employ workmen other than those of the contractor to perform and execute the work in respect of which the failure neglect or omission referred to in such notice shall have been committed or occurred. If the Governor of Gujarat shall think fit, it shall be lawful for him to enter into a new contract with any other persons, or person, for the execution of such part of the work as may not have been executed and in that event the Governor of Gujarat shall without incurring any liability to the Contractor be entitled to use all or any of the materials, tools, tackle or other things which may then be on site for the purpose of completing the work or any part thereof and to provide any additional materials, tools, or tackle required for the purpose and the cost of executing any such work and providing any such materials shall be paid by the contractor to the Governor of Gujarat on demand.

Subject to and after satisfaction of the lien of the Governor of Gujarat for any sum due to him by the Contractor for any expenses, cost or charges incurred in the completion of the work, all materials, tools, 'tackle or other thing remaining on the site and unsold after such completion shall forthwith hereafter be removed by the contractor.

14. Replacement of Defective work or material:

If during the progress of the work the Engineer shall notify in writing to the contractor that in his opinion the Contractor has executed any unsound or imperfect work, or has supplied any materials inferior in quality to those stipulated for by the Contractor, the contractor shall at his own expense, within ten days of his receiving the notice, proceed with due expedition to remove or after and reconstruct or replace the work, or as the case may be supplied fresh materials up to the standard of the specification. In place of the work or materials complained of by the notice (as the case may be) and in case the contractor shall fail to do so the Governor of Gujarat may after expiration of ten days from giving of such notice give a further notice in writing stating that the Governor of Gujarat intention so to do forthwith at the cost of the Contractor remove the work or materials complained of and perform all such work or (as the case may be) supply all such materials in place of those complained of as may be necessary or proper in order to comply with the Contractor and the cost as certified by the Engineer of any such removed and performance of work or supply of materials shall be paid by the contractor to the Governor of Gujarat on demand, provided always that nothing in this, clause shall be deemed to deprive the Governor of Gujarat or effect any other rights or remedies under the Contract otherwise which he may have in respect of such defects or deficiencies. No payment which have been made on account of materials delivered or work executed shall be looked on as acceptance of such or any work or materials.

15. Cutting away & making good :

The tender is to include all necessary cutting and making good for the purpose of the contract of the wood work, walls, floors etc. of the site. The contractor will be held responsible for, and will have to make good at his own expense. to the satisfaction of the Engineer, any damages to or disfigurement of the site which may have been caused by the acts or omissions of himself or his servants or agents in connection with the carrying out of the contract.

16. Maintenance:

The Contractor shall make good at his own' expense all defects due to faulty design material, or workmanship on the part of the contractor which may during a period of 6 calender months from the date on which the work is certified by the Engineer to have been brought into beneficial use or if no such certificate is given from the date of the final payment for the work under clause 20 (which period is hereinafter called the "the period of maintenance") develop under proper use in the work or any part thereof by replacing plant materials or work or otherwise as may be necessary. Any such making good by the contractor shall in no case relieve' him from his liability to make good any further defect in the work made good of replace which may develop during the reminder of such period of twelve months. If any such defects are clearly, caused by the fault of the Contractor and are liable to recurrence the contractor shall make such alterations as are required to prevent any recurrence of such defects. If any defects or alterations which Contractor shall become liable to make good or make under this clause be not made good or made (as the case may be) within such time as the Engineer may prescribe for the Engineer may proceed to make good or make the same (as the case may be) at the risk and expense of the Contractor; but without prejudice to any other right or remedies which the Governor of Gujarat may have against the Contractor in respect of his default in making good or making the same as aforesaid' and the cost of any such making good or making shall be paid by the Contractor to the Government of Gujarat on demand.

17. Contractor's Representative & workmen:

The contractor Shall employ at least one competent representative, whose name or names shall have previously been communicated in writing to the Engineer by the Contractor to Superintend the carrying out the works. The said representative, of if more then one shall be employed then, one of such representative, shall always be present on the site during working hours and any written orders or instruction which the Engineer or his duly authorized representative. whose name shall have been previously communicated in writing to the contractor, may give to the said representative of contractor, shall be deemed to' have been given to the contractor.

The Engineer shall be at liberty to object to any representative or person employed by the Contractor in the. execution of or otherwise about the work who in the Engineers opinion shall misconduct himself or be incompetent or negligent and. the contractor shall remove every person so objected to forthwith upon receipt from the Engineer of notice in writing requiring him to do so.

17. A Minimum age of persons employed and employment of donkeys or other animals:

- (i) The Contractor shall not employ any person who is under the age 12 years.
- (ii) The contractor shall not employ donkeys or other animals with breaching of string or thin rope. The breaching must be attest three inches side and should be tape (Nawar).
- (iii) No animal suffering from sores, lameness or emaciation or which is immature. shall be employed on the work.
- (iv) If contractor does not accept the proceeding conditions No. (i), (ii), & (iii) his tender shall not be accepted and his name shall be removed from the list of contractors.
- (v) The Engineer shall' remove from the work any person or animal found working which does not satisfy these conditions and to responsibility shall be accepted by the Governor of Gujarat for any delay caused in the completion of the work by such removal.

18. Submission of Samples:

The contractor shall not without written sanction of the Engineer use for the execution of the work any materials plant or stores of any type of description other than those specified in his tender. He shall if required to do so, or at his 'options, deposit samples, at the office of the Engineer for approval and the Engineer shall within 14 days of the receipt of the samples, express in writing to the contractor his approval or otherwise of the samples deposited and all materials. plant and stores used in the execution of the works must be in every way equal to the deposited samples. All the deposited samples will be returned to the contractor within one month of the work being taken over:

19. Deduction from contract Price:

The amount or all costs of works, expenses or other sums which under the contract shall be payable by the contractor to the Governor of Gujarat from any moneys due or becoming due by him to the Contractor under contract, without prejudice to the Governor of Gujarat, right to recover the same by the ordinary

process of law.

20. Terms of Payment:

Subject to any deduction which the Governor of Gujarat may be authorised to make under the contract, the Contractor shall be entitled upon the certificate of the Engineer to the effect hereinafter stated **payments of R.A. Bills shall be made to the contractor as per items, in measurable units executed according to the specifications.**

If, at any time the contractor shall be prevented for any period of not less than 30 days .from causes within the control of the Governor of Gujarat either first, from delivering on the site any plant or material ready in India for delivery or secondly from proceeding with the erection at any plant or materials which he had already delivered on the site. the Governor of Gujarat shall bear the cost of storage and protection, including insurance in accordance with clause II. of the plant and material during such period in the first of such of contractor shall be entitled to payment of 80% percent of the value certificate as aforesaid of the plant or materials delivery of which shall have been so prevented within one month from the date on which as certified by the Engineer such plant or material are so ready as aforesaid provided that all portions thereof have been suitably and sufficiently marked as being property of the Governor of Gujarat and are delivered into the custody of some person approved by the Engineer who has granted a receipt thereof.

Installments shall be due and payable by the Governor of Gujarat within one month from the date of each certificate of the Engineer.

21. Certificates of Engineer :

Every applications to the Engineer for a certificate must be accompanied by a detailed claim in duplicate setting forth (in the order of the Schedule for price if any) particulars of the Plant or materials delivered and work executed to the date of the claim, and the certificate as to such of the plant and, work mentioned in the claim as is in the opinion !he Engineer in accordance with the contract shall be issued within 14 days of the. application. No application for a certificate shall be made within 14 days previous applications.

22. Certificate not to affect rights of the Governor of Gujarat of contractor:

The Engineer may be any certificate make any correction or modification in any certificate previously issued. by him. any payment shall be regulated and adjusted accordingly, No certificate of the Engineer shall nor shall any payments on account by the Governor of Gujarat to the Contractor, nor extension of time for the execution of the works by the contractor which may be granted by or behalf of the Governor of Gujarat affect or prejudice any of the rights of the Governor of Gujarat against the contractor under or relieve him any of his obligations for or in respect of the due performance of the contract, or be interpreted as approval of work done or of material supplied.

23. Suspension of Work:

The Governor of Gujarat shall any to the contractor all proper expenses arising from suspensions of the works by order in writing of the Engineer or any other officer {}'1 behalf of the Governor of Gujarat unless such suspension is due of some default on the part of the Contractor or any sub-contractor under him.

24. Damages for delay in completion:

(i) If the Contractor fails to complete the work under contract by the stipulated date. he shall pay liquidated damages of Rs. 0.1 percentage of the contract value per day from the date of delaying the said work upto the date of completion and handing over to the Government".

(ii) However also if the contractor fails to complete any part of the work Proportionate to by the time in relation to the value of such part, he shall pay Liquidated damages per day from the date of delaying the said part of the work up to the date of completion of the said designated part at the rates shown in the said schedule of the contract Value of such part for such failure till the said designated part is completed.

(iii) The aggregate maximum of liquidated damages payable under this clause shall not exceed Rs. 0.1 percentage of contract value per day and shall be subject to the maximum amount of ten percent of the estimated amount put to tender.

(iv) Delays requiring payment of ten percent liquidated damages of the amount put to tender for performance shall be sufficient cause for termination of contract and for forfeiture of security deposit. (including amount of performance bond in respect of works estimated to cost more than Rs.15 lacs for performance) and registration of the contractor shall also be kept in abeyance for three years from the date as fixed in all such cases.

24-A If-the Contractor shall desire an extension of the time for completion of work on the ground of his having been unavoidably hindered in' it execution or on any other ground he shall apply in writing to the Ex. Engr. before the expiration of the period stipulated in the tender or before expiration of 30 days from the date

on which he was hindered as aforesaid on with the cause for making for extension occurred whichever, is earlier and the Ex. Engr. may if in his opinion. There are reasonable and bonafide grounds for granting, and extension grant such extension as he thinks necessary or proper. The decision of the Ex. Engr. in this matter shall be final.

No applications for extension of time for completion of work shall be considered unless it is received by registered post in the office of the Executive Engr. or left at his office and obtained receipt there of duly signed by the

Ex. Engr. or his nominee authorised in this respect.

The date of receipt of application by the Ex. Engr. shall be considered as the date of application for the purpose of counting the period as mentioned above.

24-B. "if the contractor or his workmen, or servants shall break. deface, injure or destroy and part of the building. or the work in question in/or which they may be working or any building, road fence, enclosure or glass-land .or cultivated ground contingency to the premises on which the work or any part thereof is being executed or if any damage shall be done to the work from any cause whatever before completion of the work or before the completion of the maintenance period whichever is later or any damages occurred/caused due to normal flood or rain or if any imperfection become apparent in it within three-months from the grant of a certificate of completion, final or otherwise by the Engineer-in-charge, the contractor shall make good the same at his own expenses or in default, the Engineer-in-charge may cause the same to be good by other contractor, and deduct expenses (of which the certificate of the Engineer-in-charge shall be final) from any sums that may then be due or may thereafter become due to the contractor or from his security deposit or the proceeds of sale thereof a sufficient portion thereof".

24-C Force Major Clause:

Neither party shall be liable to the other for any loss or damage occasioned by or arising out of acts of God, such as Unprecedented flood, Volcanic eruption, earthquake or other convulsion of nature and other acts such its but not restricted to general strike. invasion, the acts of foreign countries, hostilities, or war like operations before or after declaration of war. rebellion, military or Usrped power which prevent performance of the contract and which could not have been foreseen or avoided by a prudent person.

Note: "Unprecedented flood" means the flood crossing the High Flood Level of the past _____year(s) which IS on the available record.

(Modified Vide R & 8 D. G. R. No. TNC - 1096 – 1B - 143 - (16) dated .11-1-99)

25. Time of taking over:

The work shall for the purpose of all the provisions of these conditions be deemed to have been completed and taken over by the Governor of Gujarat when the Engineer, shall have certified in writing that it has been completed in accordance with the Contract conditions and such Certificate shall not be unreasonable withheld nor shall the Engineer delay its issue on account of commissions or defects which in his opinion do not effect the efficient use of the work, but such issue shall be without prejudice to the Contractor's liability to make good any such omissions and defects with the greatest possible expedition.

26. Death & Bankruptcy :

If the Contractor shall die, or become insolvent or bankrupt or have a receiving order made against him or compound with or make no proposal carrying on his business under inspection or for the benefit of his creditors. or commit an act of insolvency or bankruptcy, or being a corporation be ordered to be wound up or have a received of its business appointed the Governor of Gujarat shall be entitled forthwith by notice in writing to the Contractor his legal representatives to determine the contract and the Governor of Gujarat may in that event complete the contract in such time and manner and by such person as he shall think fit.

27. Disputes to be referred to Gujarat Public Works Disputes Arbitration Tribunal:

The disputes relating to this Contract in so far as they fall within the jurisdiction of Gujarat Public Works Disputes' arbitration tribunal shall be referred to the said Tribunal of Gujarat State.

However the reference to Arbitration Tribunal under this clause will not stay fulfillment of obligations of the contractor or rights of the Engineer-in-charge under this contract, unless otherwise ordered to the contrary by the said Tribunal as Interim Relief measure.

(The following clause is to be deemed included in this conditions only when Plant or Machinery is included in the Contract).

28. Contract Drawings:

The contractor shall submit to the Engineer for his approval on or before the dates stipulated for this purpose in the specification copies of all the drawings of the general arrangements of the plant as set out therein and of such detail drawings as may be reasonably necessary.

Within Fourteen days from the receipt, by. him of such copies the Engineer shall signify his approval or otherwise of the same and if he does not do so he shall be deemed to have approved thereof.

Within Fourteen days from the notification by the Engineer to the Contractor of his approval such

copies or in the absence of such notification within thirty days from the receipt of such copies, the copies in ink on tracing cloth or ferrogalllic prints mounted on cloth. of all drawings as approved shall be supplied to the engineer by the contractor respectively and shall thereupon be signed by the contractor and become the property of the Governor of Gujarat.

Such signed copies of the drawing shall not be departed from in any way whatsoever except with the written permission of the Engineer. During the execution of the works of the signed copies shall be always kept available for reference on the site.

In the event of the Contractor desiring to keep in his own possession a signed copy of the drawings as approved he shall supply three copies. Instead of two and in this case the Engineer shall sign the third copy and return the same to the Contractor.

29. Manner of Execution, Quality of materials etc. :

The plant shall be manufactured, constructed, provided, put in position and maintained in the best and most substantial and workmen like manner and materials of the best and approved qualities having regard to their respective uses.

30. Tests on site:

In all cases where the special conditions are provided for tests on the site whether of plant, materials or workmanship the Governor of Gujarat except where otherwise specifically stipulated shall provide free of charge such labour, materials fuel stores, apparatus and instruments as may be requisitioned from time to time efficiently to carry out such tests in accordance with the condition.

Where electrical energy is required for test\$ on site and a supply is available on the site from an existing installation such electrical energy shall be supplied to the contractor by the Govt. free of charge at the pressure and frequency of the ordinary supply is available the electrical energy necessary for such tests shall be provided by the contractor.

31. Delivery of plants & materials:

No Plant materials shall be tendered for delivery until an intimation in writing shall have been given to the contractor by the Engineer that Governor' of Gujarat is ready to take delivery.

32. Tests on completion:

On the completion of the works on the site in accordance with the contract the contractor shall give the Engineer notice in writing of such completion. The Engineer shall after receipt of such notice by notice in writing under his hand for date and an hour on that date for the making of the test on site if any such are provided for the contract.

The contractor shall carry out such tests upon the date and at the hour so fixed and if the Engineer or his authorized representative shall attend on that date at that hours such test shall be carried out in the presence of the Engineer or such representative.

If any portion of the plant fails under the tests to satisfy the contract conditions similar tests according to the contract of the portion so failing shall if required by the Engineer or by the Contractor be repeated within a time to be fixed by the Engineer and the provisions of this clause shall apply to such repeat 20 test as if they were the original tests and the contractor shall pay to the Governor of Gujarat all reasonable expenses to which he may be put by such tests.

If the tests or any repeated tests so required as aforesaid be not made by the Contractor *on* the date fixed as aforesaid for the same by the Engineer may proceed to make such test himself at the contractor's risk and expense.

If in any test under this clause the plant tested shall fail to satisfy the contract conditions the Governor of Gujarat shall as from the date stipulated by the contract for completion nevertheless have the right of using such plant until the same shall satisfy such conditions and such use shall be at the contractor's risk. In the event of the question whether the works have been completed in accordance with the contract or any question regarding such completion being submitted to Arbitration as any portion of the plant the Engineer may certify to be capable of being used on condition of paying to the contractor a sum calculated (according to the period or the use) at the rate of 5 percent per annum upon the amount withheld or deducted in respect of such plant.

33. Rejection of Defective work:

If the works, or any portion thereof shall not in the opinion of the Engineer on the stipulated tests (if any) being made in accordance with the contract satisfy the contract condition within three months after the date stipulated for completion the engineer may give notice in writing to the contractor setting for the particular of the defects of particulars in respect of which the works in his opinion fail to comply with the contract conditions and requiring the contractor to make good. after or replace the same within such time to be specified in the notice as the engineer may consider reasonable and the contractor shall make good, after or replace the same as required by such notice and so as to make it comply with the requirements of the contract condition within the time so specified. Should he fail to do so within that time the Governor of Gujarat may make good alter or replace the same as so required and the cost ,} such making alteration good or replacement (less in the case of any replacement any sum which would have become due to the contractor under the contract in respect of the works replaced and which shall) of have been paid to him) shall be paid by the contractor to the Governor of Gujarat on demand or should the Governor of Gujarat not make good, after or replace any defective works in respect of which such notice as aforesaid shall be given within ,six weeks from the date of the given of such notice the contractor shall repay to the Governor of

Gujarat all sums (if any) paid by him to the Contractor in respect of such works. Nothing contained in this clause shall prejudice or affect the rights of the Governor of Gujarat under the contract whether in the way of enforcement of penalties or otherwise in respect of any delay in the completion of this work.

34. Use of plant of works pending making good:

If at expiration of the time specified for making good, altering or replacing the plant of works in any notice given by the engineer to the contractor under the last preceding clause the contractor shall not have duly made good, altered or replaced the same in accordance with the contract the Governor of Gujarat shall be at liberty if he thinks fit to make use of the same for such time as shall be reasonably sufficient according to the circumstances to enable him, to make good after or replace the same (whichever he may see fit to do) provided that in respect of the period of such user, the Govt. of Gujarat shall not be entitled to any damages under clause 24 of these conditions and in the case of complete replacement the contractor shall be entitled to be paid in reasonable sum for the same.

35. Workman's compensation in case of injury:

The contractor shall be responsible for any compensation and shall pay to his workmen Compensation payable for injuries under, the workmen's Compensation Act, 1923 (VIII of 1923) hereinafter called the said Act. If such compensation is paid by Govt. as principal under sub-section (1) of section 12 of the said Act. on behalf of the Contractor, it shall be recoverable by Government from the contractor under sub section (2) of the said section such compensation shall be recovered in the manner laid down in clause 3 and 19 of the condition of contract.

36. The Apprentices :

The contractors shall afford or procure as the case may be every facility to Indian apprentices for practical training in the factory.

Owned managed controlled or patronized by them, so as to enable the Indian Apprentices to acquire full knowledge of the technique and work of their trade industry. calling or profession.

37. Set-off Clause :

Any sums of money due to the Contractor (including the security deposit returnable to the contractor under this contract shall be appropriated by the Government and shall be set off against any claim of the Government for the payment of sum of a money arising out of or under any other contract made by the contractor with the Government. When no such amount for purpose of the recovery from the contractor against any claim of the Government is available such a recovery shall be made from the contractor as arrears of land revenue.

38. Appointment of local labourers:

The Contractor should as far as possible obtain the requirement of labourers skilled and unskilled from the nearest employment exchange. so as to utilize the local employment potential. If there are no local employment exchange or such exchanges are not able to provide the required labourers locally, suitable local labours should be utilized to the maximum extent possible.

39. Fairwages :

If a contractor fails to pay within '7' (seven) days to the labourer (s) worker(s) the minimum wages prescribed by the Government under the Minimum Wages Act, 1949 as in force ,from time to time the Executive Engineer or the officer of a equal rank shall be at liberty to deduct the amount payable to the labourer (s) workers from his (contractor's) bill or deposit(s) payable by the contractor after making due inquiries and shall not be entitled to any payment or compensation on account of any loss that he (contractor) may have to incur of the 'action as aforesaid. Before the action as aforesaid is enforced notice in writing to the contractor shall be issued by the Executive Engineer or the officer of the equal rank to pay the wages as per minimum Wages Act in face at the relevant time. If the contractor does not act as aforesaid within seven days then the action contemplated as above shall be taken against him.

40. License for Contract Labours :

Before starting the work, the contractor will have to obtain the license from the District Assistant Labour Commissioner under the Contract Labour (Regulation & Abolition) Act, 1970 and Contract Labour (Regulation & Abolition) Gujarat Rules 1972 after paying necessary fees and deposit on the basis of the number of labourers to be employed on the work and will have to supply two true copies of the said license to the Deputy Executive Engineer before the work is started.

Signature of contractor/s

Executive Engineer
Division

Name of work :

(The details of material to be supplied departmentally)

It. No.	Item.	Qty.	Rate.	Place of Delivery.
------------	-------	------	-------	-----------------------

As per separate sheet attached

Note:-1.The intending tender/s shall verify prior to submission of tender that the rates in relevant coloumn of the above schedule are filled in by the issuing authority on the issue of blank tender form.

2.Store to be supplied to contractors for a work free of cost should be attached mentioned in schedule 'A' in addition to scheule 'B' & the specification thereto.

(Signature of Contractor)

Executive Engineer,
Baroda Electrical Division,
R&B Deptt., Baroda.

: S C H E D U L E : B :

Name of work :-

Qty.	Unit.	Sr. No.	Description.	Rate in Rs.		Per.	Amount.
				Figure	Words		

As per separate sheet attached

Total Rs. In Words

I am / We are willing to carry out the work at _____% below _____% (Should be written in figure and words) of the estimate rates mentioned above. Amount of my/our tender work out as under.:

(A) Total Tendered Amount. Rs. _____

(B) Rebate on above tender amount (if any) _____% (In Figure) Rs. _____
(Rupees _____ in words)

(C) Net Tendered Amount (A-B) Rs. _____

In Words (Rupees _____)

(a) I/We hereby declare that I/We have visited the site and fully exquisite myself/ourselves with the local situation regarding materials, labour and other factors pertaining to work before submitting tender.

(b) I/We hereby declare that I/We have carefully studied the conditions of contracts, Detailed specification and other tender document of this work and agree to execute the same accordingly.

- Note
- 1) The Rates are inclusive oall taxes, transport charges, octroi duty and storage charges upto date.
 - 2) The materials covered for wiring should be got approved from the Dy. Executive Engineer, in charge of the work.
 - 3) The materials and work shall have to be used and carried out as specification in technical note.
 - 4) All works shall be carried out as per public works Department hand book and Other specifications of the Dn. Or as directed.
 - 5) Rates are inclusive of 1% Labour cess in tender amount so 1% of total amount of bill will be deducted from the bill.

(Signature of Contractor)

Executive Engineer,
Baroda Electrical Division,
R & B Deptt., Baroda.

(1986)

GENERAL

1. Wiring Rules:

The installation generally shall be carried out in conformity with relevant Indian Standard Specifications and code of practices prevalent, Indian Electricity Rules, 1956 and Indian Electricity Act, 1910 as amended from time to time.

2. Definition:

The definition of terms shall be in accordance with Indian Standard code of Practice for Electrical wiring Installation IS- 732-1982 except for the definition of point in case of Internal Electrical Installation. For definition of point wiring and measurement of Electrical works IS-5908-1970 shall be referred to.

3. Voltage and Frequency of Supply:

All current consuming devices shall be suitable for frequency of 50 C/s and system of voltage meant for unless otherwise specified.

4. Layout of wiring and its description :

(i) The wiring shall be carried out as per Schedule "power" wiring must be in screwed conduit and shall be kept separate and distinct from lighting wiring. All wiring must be done on the distribution system with main and branch distribution boards at convenient centers and without isolated fuses. All conductors shall be run as far as possible along the walls and ceiling as to be easily accessible and capable of being thoroughly inspected. The balancing of circuits will be arranged before hand by the Ex. Engineer Electrical Division.

(ii) Within one month of the taking over the installation, the contractor shall supply to the Ex. Engineer, Elect. Division a complete set of wiring diagrams of the same on drawings to be supplied when available by the Executive Engineer, Electrical Division, and to the satisfaction of the Ex. Engineer, Elect. Dn. and these Wiring plans shall be "Drawings" within the meaning of the term as used in the General Conditions of contract.

5. Conductors:

All conductors unless otherwise specified shall not be less than 1.5 Sq. mm for point wiring and 2.5 Sq. mm for

mains Conductors for power and lighting circuits shall be of adequate size to carry the designed circuit load without exceeding the permissible thermal limits for the installation, and such sizes will be stipulated in specifications and or drawings.

6. Cables:

- 6.1 All cables shall conform to relevant Indian Standards.
- 6.2 Conductors of all cable except the flexible cable shall be of aluminium. The smallest aluminium conductors for the final circuit shall have nominal cross sectional area of not less than 1.5 Sq. mm. The minimum size of the aluminium conductors for power wiring shall be 4 sq.mm
- 6.3.1 Conductors of flexible cables shall be of copper. The minimum cross sectional area of such a cables shall be 14.0193 mm. The flexible cable shall have uniform and adequate insulation.
- 6.3.2 Unless the flexible cables and conductors are protected by armour or though rubber or PVC Sheath, these shall not be used in workshops and other places where they are liable to mechanical damage.
- 6.3.3 Core flexible cables shall be used for connecting single phase Appliances for phase, neutral & earth connections.

7. Fall of Potential:

The cross sectional area of all conductors inside buildings shall be so proportioned to their lengths that the drop in voltage between main fuses and the farthest point or any lamp shall not exceed three percent of the voltage of the consumer's With all the consuming devices in use.

- 7.1 If the CABLE SIZE is increased to avoid the voltage drop in circuit current rating of the cable shall be more than that for which the circuit is designed. In each circuit or sub circuit every cable shall have a current rating not less han that of the fuse which protects the circuit or sub circuit respectively for current higher than the full load current.

8. Ratings of lamps and fans socket out lets: Points and exhaust Ifans

- 8.1 Incandescent lamps installed in residential and non-residential buildings shall be rated at 60 watts & 100 watts respectively.
- 8.2 Table fans and ceiling fans shall be rated at 60 watts, exhaust fan shall be rated according to their capacity.
- 8.3 5 Amp. socket outlet points and 15 Amp. Sockets outlet points shall be rated at 100 watts and 1000 watts respectively for the purpose of load assessment unless actual values of the load are known or specified.

9. Tests:

- 9.1 Before the installation is commissioned following tests shall be carried out.

- (1) Insulation Resistance test
- (2) Polarity Tests of Switches
- (3) Earth continuity tests
- (4) Earth electrode Resistance test

- 9.2.1.1 The insulation resistance shall be measured between earth and the whole system of conductors or any section thereof with all fuses in place and all switches closed, and except in earthed concentric wiring all lamps in position or both poles of the installation otherwise electrically connected together a direct current pressure of not less than twice the working pressure provided that it need not exceed 500 volts for medium voltage circuits where the supply is derived from the three wire D.C. or a poly phase A.C. System, the neutral pole of which is connected to earth either direct or through added resistance, the working pressure shall be deemed to be that which is maintained between the phase conductor and the neutral.
- 9.2.1.2 The insulation resistance shall also be measured between all conductors to one pole or phase conductor of the supply and all the conductors connected to the neutral or to the other pole or phase conductors of the supply with all lamps in position and switches in 'OFF' position and its value shall be not less than that specified in Sub Clause 9.2.1.3.
- 9.2.1.3 The insulation resistance in Megohms measured as above shall not be less than 50 Megohms divided by the number of outlets or when PVC insulated cables are used for wiring 12.5 megohms divided by number of outlets
- 9.2.1.4 Where a whole installation is being tested, a lower value than that given by the formula, subject to a minimum of 1 megohm is acceptable.
- 9.2.1.5 A preliminary and similar test may be made before lamps, etc. are installed and in this event the insulation resistance to earth should be not less than 100 megohms divided by the number of outlets or when PVC insulated cables are used for wiring 25 megohms divided by number of outlets.
- 9.2.1.6 The term "Outlet" includes every switch except that a switch combined with a socket outlet, appliance or lighting fitting is regarded as one outlet.
- 9.2.1.7 Control rheostat heating and power appliance and electric sign may, if required, be disconnected from the circuit during the test, but in that event the insulation resistance between the case or frame work, and all live parts of each rheostat, appliance and sign, shall be not less than that specified in the relevant Indian Standard Specification or where there is no such specification shall be not less than half a megohm.

9.2.2 Polarity Test :

- 9.2.2.1 In a two wire installation a test shall be made to verify that all switches in every circuit have been fitted in the same conductor through out & such conductor shall be labeled or marked for connection to the phase conductor or to the non-earthed conductor of the supply
- 9.2.2.2 In a three wire or a four wire installation a test shall be made to verify that every non-linked single pole switch is fitted in a conductor which is labeled or marked for connection to one of the phase conductors of the supply.
- 9.2.2.3 The installation shall be connected to the supply for testing. The terminals of all switches shall be tested by a test lamp one lead of which is connected to the earth. Glowing of test lamp to its full brilliance when the switch is in 'on' position irrespective of appliance in position or not shall indicate that the switch is connected of the right polarity,

9.2.3 Earth Continuity Test :

The earth continuity conductor including metal conduits and metallic envelopes of cables in all cases shall be tested for electric continuity and the electrical resistance of the same along with the earthing lead but excluding any added resistance or earth leakage circuit breaker measured from the connection with the earth electrode if any point in the earth continuity conductor in the completed

installation shall not exceed one ohm.

9.2.3.1 Earth Electrode Resistance Test :

Earth electrode Resistance test may be carried out by Meggar Earth Testers containing a direct reading ohm-meter a hand driven generator and auxiliary electrodes

- 9.3 On completion of an electric installation (addition and alteration) a certificate shall be furnished by the contractor countersigned by the certified Supervisor under whose direction supervision the installation was carried out. This certificate shall be in the prescribed form as given in Appendix-'B' in addition to the test certificate: required by Local Electrical Supply Authorities.

10. Joint and looping back:

Unless with the sanction of Ex, Engineer Electrical Divisions all joints in conductor shall be means of approved mechanical connectors in suitable and approved junction boxes but looping back system shall be preferable. In wiring unless otherwise specified Phase and live conduct shall be looped at the switch box where a neutral conductor can be looped from light. fan or socket. In non-residential buildings, neutral and earth continuity wire shall be brought to each of the switch boards should be of adequate size to accommodate at least one number of 5 Amps socket outlet and control switch in future.

11. Switches :

Main Switch gears, Switch Board and their location:

- 11.1 All main switches (other than those of iron clad pattern) carrying current of 10 Amp. and above shall be fitted for back connections and shall be suitably protected.
- 11.2 All switches and circuit breakers shall be constructed in accordance with the I.S. 4237-1967. General requirement for switchgear and control gear for voltage not exceeding 1000 Volts and other relevant I.S.. provided also that, spring shall be either of phosphor bronze or if steel shall be copper or Nickel plated and that handle shall be so fastened that they do not tend to unscrew or become loose.
- 11.3 All main switches shall be either of metal clad enclosed pattern or of any insulated enclosed pattern which shall be fixed at close proximity to the point of entry of supply.
- 11.4 Switch boards shall not be erected above gas. stoves', or sinks or within 2.5 m of any washing unit in the washing rooms of laundries or in the bath rooms, lavatories. toilets or kitchens.
- 11.5 Switch boards, if unavoidably fixed in places likely to be exposed to weather. to drip or to abnormal moist temperature the outlet casing shall be weather proof and shall be provided with glands or bushing of adopted to receive screwed conduit according to the manner in which cables are run, PVC and double flanged bushes shall be fitted in the holes of the switches for entry and exit of wires.
- 11.6 A switch board not be installed so that its bottom is within 1.25 m above the floor unless the front of the switch board is completely enclosed by a door or the switch board is located in a position to which only authorised persons have access.
- 11.7 Switch boards shall be recessed in the wall if so specified in the schedule of work or in the special specification. The front shall be fitted with hinged panel of other suitable material such as bakelite in wood frame with locking arrangement. the outer surface of door being flush with the walls. Ample room shall be provided at the back for connections and at the front between the switchgear mountings and the door.
- 11.8 Equipments which are on the front of a switch board shall be so arranged that inadvertently personal contact with live parts is unlikely during the manipulation of switchgears, changing of fuses or like operations.
- 11.9 No holes other than the holes by means of-which the panel is fixed shall be drilled closer than 1.3 cms. from any edge of the panel.
- 11.10 The various live parts, unless they are effectively screened by substantial barriers of non-hydroscopic, no-inflammable insulating material, shall be so spaced that space shall not be maintained between such parts and earth.
- 11.11 The arrangement of gear shall be such that they shall be readily accessible and their connections to all instruments and apparatus shall also be traceable.
- 11.12 In every case in which switches and fuses are fitted on the same pole, these fuses shall be so arranged that the fuses are not alive when their respective switches are in the off position.
- 11.13 No fuses other than fuses in instrument circuit shall be fixed on the back of or behind a switch board panel or frame.
- 11.14 All the metal switchgears and switch boards shall be painted, prior to erection with one coat of

- antirust primer, After erection they shall be painted with two coats of approved enamel or aluminium paint as required on all sides wherever accessible.
- 11.15 All switch boards connected to medium voltage and above shall be provided with 'Danger Notice Plate' conforming to relevant Indian Standards.

12. Control at Point of Commencement of Supply:

- 12.1 There shall be a linked main switchgear with fuse on each live conductor of the supply mains at the point of entry. The wiring through out the installation shall be such that there is no break in the neutral wire except in the form of a linked switchgear. The neutral shall also be distinctly marked. In this connection Rule 32(2) of the Indian Electricity Rules, 1966 (See Appendix- 'A') shall also be referred.
- 12.2 The main switchgear shall be situated as near as practicable to be termination of service line and shall be easily accessible without the use of any external aid.
- 12.3 On the main switchgear, where the conductor of a two wire system or an earthed neutral conductor of a multi-wire system or a conductor which is to be connected thereto, an indication of a permanent nature shall be provided to identify the earthed neutral conductor. In this connection Rule 32(1) of Indian Electricity Rules, 1956 (see appendix. 'N') shall be referred.

13.0 Switch Board & Distribution Boards:

Metal clad switch gear shall preferably be mounted on any of the following types of Board.

13.1 Hinged type Metal Boards:

- 13.1 These shall consist of a box made of sheet metal not less than 2 mm thick and shall be provided with a hinged cover to enable the board to swing open for examination of the wiring at the back. The joints shall be welded. A teak wood board, thoroughly protected both inside and outside with good insulating varnish conforming to IS : 1347-1952 specification for varnish shellac, for General purpose and of not less than 6.5 mm thickness, shall be provided at the back for attachment of incoming and outgoing cables. There shall be a clear distance of not less than 2.9 cm between the teak wood board and the cover, the distance being increased for larger boards in order that on closing of the cover, the insulation of the cables is not subjected to damage and no short length of cables is subjected to excessive twisting or bending in any case. The board shall be securely fixed to the wall by means of lag bolts, plugs or wooden Gutties and shall be provided with a locking arrangement and an earthing stud. All wires passing through the metal board shall be bunched. Alternatively, hinged type metal boards shall be made of sheet covering mounted on channel or angle iron frame.

Note: Such type of boards are particularly suitable for small switch-boards for mounting metal-clad switchgear connected to supply at low voltages.

13.2 Fixed type Metal Boards:

These shall consist of an angle or channel of iron frame fixed on the wall or on floor and supported on the wall at the top if necessary. There shall be a clear distance of one metre in front of the switch board. If there are attachments of base connections at the back of the switch board Rules 51 (1) (c) of Indian Electricity Rules, 1956 shall apply.

Note : Such type of boards are particularly suitable for large switchboard for mounting large number of switchgears or higher capacity metal clad switchgears or both.

13.3 Teakwood Boards:

- For small installations connected to a single phase 230 volts supply teak wood boards may be used as main boards or sub-board. These shall be of seasoned teak or other durable wood with solid back impregnated with varnish of approved quality with all joints dovetailed.
- 13.4 In large size medium voltage installations, before proceeding with the actual construction of the boards, a proper drawing showing the detailed dimensions and design including the disposition of the mountings, which shall be symmetrically and neatly arranged for arriving at the overall dimensions, shall be prepared and approved by the Engineer-in-charge. .

13.5 Recessing of Boards:

Where so specified the switch boards shall be recessed in the wall. The front shall be fitted with a hinged panel of teak wood or other suitable materials, such as bakelite, or with unbreakable glass doors in teak wood frame with locking arrangement, the other surface of the doors being flush with the walls. Ample room shall be provided at the back for connection and at the front between the switchgear mountings.

13.6 Arrangement of Apparatus:

- a) Equipment which is on the front of a switch board shall be so arranged that inadvertently personal contact with live parts is unlikely during the manipulation of switches, changing of fuses or like operation.
- b) No apparatus shall project beyond any edge of panel .No fuse body shall be mounted within 2.5 cm. of any edge of the panel and no hole other than holes by means of which the panel is fixed shall be drilled closer than 1.3 cms from any edge of the panel.
- c) The various live parts, unless they are effectively screened by substantial barriers of non-hydroscopic, non--flammable insulating material, shall be so spaced that an arc cannot maintain between such parts and earth.
- d) The arrangement of the gear shall be such that they shall be readily accessible and their connections to all instruments and apparatus shall also be easily traceable.
- e) In every case in which switches and fuses are fitted on the same pole, these fuses shall be so arranged that the fuses are not alive when their respective switches are in the 'OFF' position.
- f) No fuses other than fuses instrument circuit shall be fixed on the back of or behind a switchboard pannel or flame.

13.7 Marking of Apparatus :

- a) Where a boards is connected to voltage higher than 250 volts, all the apparatus mounted on it shall be marked in the following, colours to indicate the different poles or phases to which the apparatus or its different terminals may have been connected.

Alternating Current

Three-phase-red,

Yellow, & blue,

Natural-black

Direct Current

Three wire system-2 outer wires

Positive red & negative blue

Natural-black

Where fuse-wire three phase wiring is done, the neutral shall be in one Colour and the other three wires in another colour.

- b) Where a board has more than one switch each such switch shall be marked to indicate which section of the installation it controls.
- c) All markings required under the rule shall be clear permanent.

13.7.A Main & Branch Distribution Board:

13.8.1 Main and branch distribution boards shall be of any type mentioned in 13.1

13.8.2 Main distribution boards shall be provided with a switch or air circuit breaker on each pole of each circuit, a fuse on the phase or live conductor and a link on the neutral or earthed conductor of leach circuit. The switches shall always be linked.

13.8.3 Branch Distribution Board:

13.8.3.1 Branch distribution boards shall be provided with a fuse or a miniature circuit breaker or both the adequate rating setting chosen on the live conductor of each circuit and the earthed neutral conductor shall be connected to a common link and be capable of being disconnected individually for testing purposes. At least one spare circuit of the same capacity shall be provided on each branch distribution board.

13.8.3.2 In residential installations, lights and fans may be wired on a common circuit such sub circuit shall not have more than total of ten points of lights, fans and socket outlets. The load of such circuit shall be restricted to 800 watts. If a separate fan circuit is provided, the number of fans in the circuit shall not exceed ten. Power sub-circuits shall be designed according to the load but in' no case shall there be more than two outlets on each sub-circuits.

13.8.3.3 In industrial and other similar installations requiring the use of group control of switching operation, circuits, for socket outlets may be kept separate from fans and lights. Normally fans and lights may be wired on a common circuit, however, if need is felt separate circuits may be provided for the two. The road on any low voltage sub-circuit shall not exceed 3000 Watts. In case of new installation, all circuits and sub-circuits shall be designed by making provision of 20. per cent increase in load due to any future modification. Power sub-circuits shall be designed according to the load .but in no

case shall there be more than four outlets in each sub- circuits.

13.9 Installation of Distribution Boards :

- 13.9.1 The distribution fuse-boards shall be located as near as possible to the center of the load they are intended to control.
- 13.9.2 These shall be fixed on suitable stanchion or wall and shall be accessible for replacement of fuses.
- 13.9.3 These shall be of either metal-clad type, or all insulated type. But. if exposed to weather or damp situations, they shall be of the weather proof type and, if installed where exposed to explodes to explosive dust, vapour or gas, they shall be of flame proof type.
- 13.9.4 Where two or more distribution fuse boards feed low voltage these distribution boards shall be :
 - (1) Fixed not less than 2 m apart or,
 - (2) Arranged so that it is not possible to open two at a time, namely they are interlocked and the metal case is marked 'Danger 415 Volts', or
 - (3) Installed in a room or enclosure accessible to only authorised persons.
- 13.9.5 All distribution boards shall be marked 'Lighting', 'Power', as the case may be and also marked with the voltage and number of phases of the supply. Each shall be provided with a circuit list giving details 'of each circuit which it controls .and the current rating of the circuit and size of fuse-element.
- 13.9.6 Triple pole distribution boards shall not be generally used for final circuit distribution unless specific approval of Engineer- in-charge is obtained. In special cases where use of Triple pole distribution boards are inevitable they. shall be of H.R.C. fuse type only.

13.10 Wiring and Distribution Board:

- 13.10.1 In wiring a branch board, total load of the consuming devices shall be divided, as far as possible, evenly between the number of ways of the boards leaving the spare circuit for future extension.
- 13.10.2 All connections between pieces of apparatus or between apparatus and terminals on a board shall be neatly arranged in a definite sequence following the arrangement of the apparatus mounted thereon, avoiding unnecessary crossing.
- 13.10.3 Cables shall be connected to a terminal only by soldered or welded or crimped lugs using suitable sleeve, lugs or ferrules unless the terminal is of such a form that it is possible to securely clamp them without the cutting away of cable strands.
- 13.10.4 All bare conductor shall be rigidly fixed in such a manner that a clearance of at least 2.5 cms. is maintained between conductor of opposite polarity or phase and between the conductors and any material other than insulating material.
- 13.10.5 If required, a pilot lamp shall be fixed and connected through on independent single-pole switch and fuse to the bus bars of the board.
- 13.10.6 In a hinged type board, the incoming and outgoing cables shall be fixed at one or more points according to the number of cables on the back of the board leaving suitable space in between cables and shall also, if possible be fixed at the corresponding points on the switch board panel. The cables between these points shall be arranged to form a "U" or "S" shaped loop which shall be of such length as to allow the switch board panel to swing through an angle of not less than 90°.

14.0 Capacity of Circuits :

- 14.1 Lights and fans may be issued on a common circuits and such a circuit shall not have more than a total of ten points of lights, fan and socket outlets, or a load of 800 watts whichever is less. The power circuits shall be designed with a maximum of two outlets per circuits generally when load is not known or specified. In non-residential buildings at important District centers however one outlet per circuit may be preferred. The circuit shall be designed based on the loading of the circuit where not specified the load shall be taken as 1 KW per outlet, Where the load is more than 1 KW it should be controlled by a isolator switch or miniature circuit breaker.

15.0 Passing Through Walls and Floors:

- 15.1 Where conductors pass through walls one of the following methods shall be employed. Care shall be taken to

see that wires pass very freely through protective pipe or box and that the wires pass through in a straight line without any twist or cross in wires, on other ends of such holes.

- (a) A teak wood box extending through the whole thickness of the wall shall be buried in the wall and casings or conductors shall be carried so as to allow 1 .3 cms air space on three sides, of the casing conductor.
- (b) The conductor shall be carried either in a rigid steel conduit conforming to *IS: 1653-1964 specification for Rigid Steel conduits of Electrical wiring (Revised) or a rigid non- metallic conduit conforming to *18 : 2509 1963 specification for Rigid Non-Metallic conduits for Electrical Installations, or in a porcelain tube- of such size which permits easy drawing in, The end of conduit shall be neatly bushed with porcelain, wood or other approved material.
- (c) Insulated conductors while passing through floors shall be protected from mechanical injury by means of rigid steel conduit (see *18 1653-1964) to a height not less than t.5 m above the floors and flush with the ceiling below. This steel conduit shall be earthed and securely bushed.

15.2 Where a wall tube passes outside a building so as to be exposed to weather, the outer end shall be belt mounted and turned down wards, and properly bushed on the open end.

16.0 Fixing to Walls and Ceilings:

Plugs for ordinary walls or ceilings shall be of well seasoned teak or other approved hardwood- not less than 5 cm long 2.5 cm. square on the inner end and 2 cm. square on the outer end. They shall be cemented into walls to width 7.5 mm of the surface, the remaining being finished according to the nature of the surface with plaster or lime punning.

16.1 Where owing to irregular crossing or other reasons the plugging of the walls or ceiling with wood plugs presents difficulties, the wood casing, wood batten, metal conduit, or cleat (as the case may be) shall be attached to the wall or ceiling in an approved manner. In the case of new building, wherever possible teak wood plugs shall be fixed in the walls before they are plastered.

16.2 To achieve neatness, plugging of walls or ceiling may be done by an approved type of asbestos, metallic or a fiber fixing plug.

17.0 Branch Switches:

Where the supply is derived from a three-wire or four-wire source, and distribution is done on the two wire system, all branch switches shall be placed in the outer or live conductor of the circuit and no single-phase switch or fuse shall be inserted in the middle wire, earth or earthed neutral conductor of the circuit. Single-pole switches (Other than for multiple control) Caring not more than 15 amperes may be of tumbler type which shall be 'CN' when the handle known is down.

18.0 Fittings:

Where conductors are required to be threaded through tubes or channels formed in the metal work of fittings these must be free from sharp angles or projecting edges and such size that will enable them to be wired with the conductors used for the final sub Circuits without removing the boarding, taping or outer covering. As far as possible, all tubes and channels should be of sufficient size to permit 'Looping back; of wires .cables and flexible cords other than those designed for high temperature shall not be used for wiring fittings except for portable fit tings. All fittings must have not less than a half inch male nipple. Fittings and lamp holders for gas filled lamps shall be adequately ventilated.

18.1 Where light fitting is supported by one or more flexible cords, the maximum weight to which the twin flexible cords may be subjected shall be as follows:

Nominal cross sectional Area cord. mm ²	No. & Dia in mm of wires.	Max. Permissible Weight Kg.
0.5	16/0.2	1.7
0.75	24/0.2	2.6
1.0	32/0.2	3.5
2.5	48/0.2	5.3
3.5	80/0.2	8.8
4	128/0.2	14.0

- 18.2 No inflammable shade shall form a part of light fitting unless such shade is well protected against all risks of fire. Celluloid shade or light fitting shall not be used under any circumstances.

18.3 Fitting of Wire :

The use of fitting wire shall be restricted to the internal wiring and the lighting fittings. Where fitting wire is used for wiring, for the sub-circuit" loads shall be terminated in a ceiling zone or connector from which they shall be carried into the fittings.

19.0 Lamp Holders :

Lamp holders for use on brackets and the like shall be in accordance with *IS : 1258-1967, specification for Bayonet lamp holders and all those for use flexible pendants shall be provided with cord grips. All lamp holders shall be provided with shade carriers. Where center contact edison screw lamp holders are used, the outer or screw contacts shall be connected to the middle wire, the natural, and the earthed conductor .of the circuit.

20.0 Outdoor Lamps:

External and road lamps shall have weather proof fittings of approved design so as to effectively prevent the admission of moisture. An insulating distance piece of moisture proof materials shall be inserted in the fittings. Flexible cord and cord grip lamp holders shall not be used where exposed to whether. In verandahs and similar exposed situations where pendants are used, they shall be of fixed rod type.

21.0 Lamps:

All incandescent lamps, unless otherwise required and suitably protected, shall be hung at a height of not less than 2.5 m above the floor level. They shall be in accordance with IS : 418 : 1957 specification for Tungsten Filament General Service electric lamps.

22.0 Fans, Regulators and Clamps:

22.1.0 Ceiling fans :

Ceiling fans including their suspension shall conform to *IS 374-1960 specification for electric ceiling fans and regulators (Revised) & to the following requirements:

- (a) All ceiling fans shall be wired to ceiling roses or to special connector boxes, to which fans rod wires shall be connected and suspended from hooks or shackles with insulators between hooks and suspension rods. There shall be no joint in the suspension rod, but if joints be avoidable then such joints shall be screwed to special couplers of 5 em minimum length and both ends of pipes shall touch together within couplers, and shall in addition be secured by means of split pins; alternatively, the two pipes may be welded.
- (b) Fans clamps shall be of suitable design according to the nature of construction of ceiling on which these clamps are fitted. In all cases fan clamps shall be fabricated from tested new metal of suitable sizes and they shall be as close fitting as possible. Fan clamps for reinforced concrete roots shall be buried with the casting and due care shall be taken that they shall serve the purpose. Fan clamps for wood beams shall be of suitable flat iron fixed on two sides of the beam and according to the size and section of the beam one or two mild steel bolts passing through the beam shall. hold both flat irons together. Fan clamps for steel joint shall be fabricated from test~ flat iron to fit in rigidly to the bottom flange of the beam. Care shall be taken during fabrication that the metal does not crack while hammering to shape. Other fan clamps shall be made to suit the position, but in all cases care shall be taken to see that they are rigid, and safe.

Note: All fan clamps shall be so fabricated that fans revolve steadily.

- (c) Canopies on top and bottom of suspension rod shall effectively hide suspensions and connections to fan motors, respectively.
- (d) The lead-in-wire shall be of nominal cross-sectional area not less than 1.0 mm^2 with copper and 1.5 mm^2 with aluminium and shall be protected from abrasion.
- (e) Unless otherwise specified, the clear distance between the ceiling fan and the floor shall be less than 2.75 m.

22.2.0 Exhaust Fans :

For fixing of an exhaust fan, a circular hole shall be provided in the wall to suit the size of the frame which shall be fixed by means of rag-bolts embedded in the wall. The hole shall be neatly plastered

with cement and brought to the original finish of the wall. The exhaust fan shall be connected to exhaust fan point which shall be wired as neat to the hole as possible by means of a flexible, cord, care being taken that the blades rotate in the proper direction.

23.0 Attachment of fittings and accessories:

23.1 In other than conduit wiring, all ceiling crosses, brackets, pendants and accessories attached to walls or ceilings shall be mounted on substantial teak wood block twice Varnished after all fixing holes are made in them. Blocks shall be not less than 4 cms. deep, Brass screws only shall be used for attaching fittings and accessories to their base blocks.

24.0 Interchangeability :

Similar part of all switches, lamp holders, distribution fuse-boards ceiling roses, brackets, pendants, fans and all other fittings of the same type shall be interchangeable in each installation.

25.0 Conduit Wiring System:

25.1.1 **Type and size of conduit** - All conduit pipes shall be conforming to *IS : 1653-1964, furnished with galvanised or stove enameled surface. All conduit accessories shall be of threaded type and under no circumstances pin grip type or clamp type accessories be used. No steel conduit less than 16 mm in diameter shall be used. The number of insulated conductors that can be drawn into rigid steel conduit are given in Table II.

25.1.2 **Bunching of cables** - Unless otherwise specified, insulated conductors of AC supply and DC supply shall be bunched 'in separate conduits.

25.1.3 Conduit-joints-Conduit pipes shall be joined by means of screwed couplers and screwed accessories only (*IS : 2667-1964).

Specification for Fittings for Rigid Steel Conduits for Electrical Wiring). In long distance straight runs of conduit, inspection type couplers at reasonable intervals shall be provided or running threads with couplers and jam-puts (in the latter case the bare threaded portion shall be treated with anti-corrosive preservative) shall be provided. Thread on conduit pipes in all cases shall be between 11 mm to 27 mm long sufficient to accommodate pipes to full threaded portion of couplers or accessories. Cut ends of conduit pipes shall have no sharp edges nor any burrs left to avoid damage to the insulation of conductors while pulling them through such pipes;

TABLE-II MAXIMUM PERMISSIBLE NUMBER OF 250-V
GRADE SINGLE CORE CABLES THAT CAN BE DRAWN INTO
RIGID STEEL CONDUIT

(CLAUSE 6.5.1.1)

Size of cable		Size of conduit (mm)													
Nominal	Number	16		20		25		32		40		50		63	
Crossectional and area.	Diameter in mm of wires	(No. of cable Max)													
		S	B	S	B	S	B	S	B	S	B	S	B	S	B
1.0	1/1.12	5	4	7	5	13	10	20	14						
1.5	1/1.40	4	3	7	5	12	10	20	14						
2.5	1/1.80	3	2	6	5	10	8	18	12						
4)	1/1.24 I (311.06*) (7/0.85)	3	2	4	3	7	6	12	10						
6)	1/2.80 7/1.06*)	2	-	3	2	6	5	10	8						
10)	1/3.55+ 7/1.40*	-	-	2	-	5	4	8	7						
		-	-	2	-	4	3	6	5	8	6				

1 6 2 5 3 5)	7/1.70	-	-	-	-	2	-	4	3	7	6				
)	7/2.24	-	-	-	-	-	-	2	-	4	3	7	6	9	7
)	7/2.50	-	-	-	-	-	-	-	-	2	-	5	4	6	5
50)	7/3.00+	-	-	-	-	-	-	-	-	2	-	5	4	6	5

* For Cu. Conductors only.

+For Al. Conductors only.

NOTE : 1. The cable shows the maximum capacity of conduits for the simultaneous drawing-in of cables. The table applies to 250 volts grade cable. The columns headed 'S' apply to runs of conduit which have distance not exceeding 4.25mm between draw in boxes, and which do not deflect from the straight by angle of more than 15°. The columns headed 'B' apply to runs of conduit which deflect from the straight by an angle of more than 15°.

NOTE: 2 In case of inspection type draw-in box has been provided and if the cables is first drawn through one straight conduit, then through the drawn box, and then through the second straight conduit, such systems may be considered as that of a straight conduit even if the conduit deflects through the straight by more than 15°.

25.1.4 **Protection against dampness** In order to minimise condensation or seating inside the tube, all outlets of conduit system shall be properly drained and ventilated, but in such a-manner as to prevent the entry of insects as far as possible.

25.1.5 **Protection of conduit against rust** - The outer surface of the conduit pipes, including all bends, unions, tees junction boxes, etc., forming part of the conduit system shall be adequately protected against rust particularly when such system is exposed to weather. In all cases, no bare threaded portion of conduit pipe shall be allowed unless such bare threaded portion is treated with anti-corrosive preservative or covered with approved plastic compound.

25.1.6 **Fixing of conduit** - Conduit pipes shall be fixed by heavy gauge saddles, secured to suitable wood plugs or any other approved plug with screws in an approved manner at an interval of not. more than one meter but on either side of couplers or bends or similar fittings, saddles shall be fixed at a distance of 30 cm. from the center of such fittings.

25.1.7 **Bends in conduit** - All necessary bends in the system including diversion shall be done by bending pipes, or by inserting suitable solid or inspection type normal bends, elbows or similar fittings; or by fixing cast iron inspection boxes whichever is more suitable. Conduit fitting shall be avoided as far as possible. On conduit system exposed to weather, where necessary, solid type fitting shall be used. Radius of such bends in conduit pipes shall be not less than 7.5 cm. No length of conduit shall have more than the equivalent of four quarter bends from outlet, the bends at the outlets not being counted.

25.1.8 **Outlets** - All outlets for fitting switches etc., shall be boxes, of suitable metal or any other approved outlet boxes for other surface mounting or flush mounting system.

25.1.9 **Conductors**- All conductors used in conduits wirings shall preferably be stranded. No single -core cable or nominal Cross- sectional area greater than 130 mm² shall be enclosed 'in a conduit and used for alternating current.

25.1.10 **Erection and earthing of conduit** - The conduit of each circuit or section shall be completed before conductors are drawn in. The entire system of conduit and permanently connected to earth conforming to the requirements specified under pipe in a workman like manner for a perfect continuity between each wire and conduit. Gas or water pipe~ shall not be used as earth medium. If conduit pipes are liable to mechanical damage, they shall be adequately protected.

25.2 **Recessed Conduit wiring system with Rigid Steel conduits** - Recessed conduit wiring system shall comply with all the requirements for surface conduit wiring system specified in 6.5.1.1 to 6.5.1.1 0 and in addition, conform to the requirements specified in 6.5.2.1 to 6.5.2.4.

25.2.1 **Making of chase** - The chase in the wall shall be neatly made and be of ample dimensions to permit the conduit to be fixed in the manner desired. In the case of buildings under construction, chases shall be provided in the wall, ceiling etc., at the time of their construction and shall be filled up neatly after erection of conduit and brought to the original finish of the wall.

25.2.2 **Fixing of conduit in chase.** The conduit pipe shall be fixed by means of staples or by means of saddles not more than 6G cm. apart. Fixing of standard bends or elbows shall be avoided as far as practicable and all curves maintained by bending the conduit pipe itself with a large radius which will permit easy drawing-in of conductors. All threaded joints of rigid steel conduit shall be treated with some approved preservative compound to secure protection against rust.

- 25.2.3 **Inspection boxes** – Suitable inspection boxes shall be provided to permit periodical inspection and to facilitate removal of wires, if necessary. These shall be mounted flush with the wall. Suitable ventilating holes shall be provided in the inspection box covers.
- 25.2.4 **Type of accessories to be used** - All outlets such as switches and wall sockets, may be either of flush mounting type or surface mounting type.
- (a) **Flush mounting type** - All flush mounting outlets shall be of cast iron mild steel boxes with a cover of approved insulating material or shall be a box made of a suitable insulating material. The switches and other outlets shall be mounted on such boxes as would be approved. The metal box shall be efficiently earthed with conduit by an approved means of earth attachment.
- (b) **Surface mounting type** - If surface mounting type outlet box is specified, it shall be of any approved insulating material and outlet mounted in an approved manner.

25.25 When crossing through expansion joints in buildings, the conduit sections across the joint may be through flexible conduits of the same size as the rigid conduit.

25.3 Conduit Wiring System with Rigid Non-Metallic Conduits:

Rigid Non-Metallic conduits are used for surface, recessed and concealed conduit wiring.

- 25.3.1 **Type and size** - All non-metallic conduits used shall conform to IS : 2509-1963 and shall be used with the corresponding accessories (See IS : 3419~ 1965) specification for Fittings for Rigid Non-Metallic Conduits).
- 25.3.2 **Bunching off cables** - Conductors of AC supply and DC supply shall be bunched in separate conduits. The number of insulated cables that may be drawn into the conduits are given in Table III. In this table space factor does not exceed 40 percent.

TABLE-III MAXIMUM PERMISSIBLE NUMBER OF 250 VOLTS GRADE SINGLE- CORE CABLE THAT MAY BE DRAWN INTO RIGID NON-METALLIC CONDUITS

Size of cable		Size of conduit (mm)					
Nominal Cross sectional area mm ²	No. Diameter in mm of wires	16	20	25	32 (No. of cable Max)	40	50
1.0	1/1.12*	5	7	13	20	-	-
1.5	1/1.40	4	6	10	14	-	-
2.5	1/1.80 3/1.06*	3	5	10	14	-	-
4	1/1.24 7/0.85*	2	3	6	10	14	-
6	1/2..80 7/1.06*	-	2	5	8	11	-
10	1/3.55+ 7/1.40*-	-	-	4	7	9	-
16	7/1.70	-	-	2	4	5	15
25	7/2.24	-	-	-	2	2	6
35	7/2.50	-	-	-	-	2	5
50	7/3.00+ 19/1.80	-	-	-	-	2	3

* For Cu. Conductors only.

+For Al. Conductors only.

- 25.3.3 **Conduit joints** - shall be joined by means of screwed or plain couplers depending on whether the conduits are screwed or plain. Where there are long runs of straight conduit. Inspection type couplers shall be provided at intervals. For conduit fittings and accessories reference may be made to IS : 3419-1965.
- 25.3.4 **Fixing of conduits** -The provision of 25.1.6 shall apply except that the spacing between saddles or supports is recommended to be 60 cms for rigid non-metallic conduits.
- 25.3.5 **Bends in conduit** - Wherever necessary, bends or diversions may be achieved by bending the conduits (See

- 6.5.3.9) or by employing normal bends, inspection bends, inspection boxes, elbows or similar fittings.
- 25.3.6 Conduit fittings shall be avoided, as far as possible on outdoor system.
- 25.3.7 **Outlets** - All the outlets for fittings, switches, etc.. shall be boxes of substantial construction. In order to minimise condensation or sweating inside the conduit, all outlets of conduit system shall be properly drained and ventilated, but in such a manner as to prevent the entry of insects: etc. as far as possible.
- 25.3.8 For use with recessed conduit wiring system the provisions of 6.5.2.1 to 6.5.2.4 shall apply.
- 25.3.9 Heat may be used to soften conduit for bending and forming joints in case of plain conduits. As the material softens when heated, fitting of conduit in close proximity to hot surfaces should be avoided. Caution should be exercised in the use of the conduit in locations where the ambient temperature is 50°C or above. Use of such conduits in place where ambient temperature is 60°C or above is prohibited.

PVC INSULATED AND P. V.C. SHEATHED OR T.R.S. WIRING SYSTEM

26.0 GENERAL :

This system of wiring, is suitable for low pressure installation, and shall not be used in places exposed to sun and rain nor in damp places, provided they are sheathed in the special approved protective covering and well protected to withstand dampness.

26.1 Attachment to walls and ceiling :

- 26.1.1 All cables on brick walls, stone or plastered walls and ceiling shall be run on well seasoned, perfectly straight and well seasoned, perfectly straight and well varnished on four sides, teak wood or any approved hardwood battens not less than 10 mm finished thick, width of which shall be such as to suit total width of cables laid on the batten, prior to election, these shall be painted with one coat of varnish or approved paint of colour to match with surrounding. These battens shall be secured to wall and ceilings by flat head wood screws to raws plug or Phil plug at an interval not exceeding 75 cm. Wood plug can be used only with special approval of the Engineer-in-charge. The flat head wood screws shall be counter within wood batten and smoothed down with file.
- 26.1.2 Where wiring is to be carried out along the face of the rolled steel joints a wooden batten of adequate width shall first be laid on the same and dipped to it as inconspicuously as possible. The wiring should then be fixed to this backing shall be suitably bushed to prevent the abrasion of the cables.
- 26.1.3 Attachment to false ceiling : In no case, the open wiring shall be run above the false ceiling without the approval of Engineer-in-charge.
- 26.20 Link clips: Only aluminium alloy clips/joint clips shall be used. The thickness shall be 0.32 mm (30 SWG) for lengths of 25 mm to 40 mm and 40 mm (28 SWG) for lengths of 50 mm to 80 mm. The width shall not be less than 8 mm in all these cases. Link clips/joint clips shall be so arranged that one single clip shall not hold more than two core or three single core TRS of PVC insulated and PVC sheathed up to 2.5 sq. mm above while a single clip shall hold a single twin core or two single core cables. The clips shall be fixed on varnished wood batten with iron pins and space at interval of 15 cm both in the case of horizontal and vertical runs.
- 26.3.0 Bends in wiring : The wiring shall not in circumstances be bent so as to form an abrupt right angle but must be rounded off at the corners to a radius not less than six times the overall diameter of the cable.
- 26.4.0 Protection of wiring from Mechanical Damage:
- 26.4.1 In cases where there are chances of any damage to wiring, such wiring shall be drawn complying with all the requirements of conduit -wiring system.
- 26.4.2 Such protective covering shall in all cases be fitted on all down drops within 1.5 m from the floor, or from floor level up to the switch board whichever is less.
- 26.5.0 Passing through floors: All cables taken through floor shall be enclosed in heavy gauge steel conduit extending 1.5 m above the floor or up to the switch board whichever is less and flush with the ceiling below or by means of any approved type of metallic covering. The ends of all conduits or pipes shall be neatly bushed with porcelain wood or other approved material. The conduit pipes, shall be securely earthed.
- 26.6.0 Passing through walls: When conductors pass through walls, any one of the following methods shall be employed. Care should be taken to see that wires pass very freely through protective pipe or box and that wires pass through in a straight line without any twist or cross in wires on either ends of such holes.

- (a) A box of teak wood or approved hard wood extending through the hole thickness of the wall shall be buried in the wall and casings or conductors and casing or conductors shall be carried so as to allow 1.3 cm air space on the three sides of the casing or conductor.
 - (b) The conductors shall be carried in an approved heavy gauge solid drawn or lap weld conduit or in a porcelain tube of such a size. that it permits easy drawing in, the ends of conduit shall be neatly bushed with porcelain, wood or other approved material,
- 26.6.1 Where a wall tube passes outside a building so as to be exposed to weather, the outer end shall be mounted and turned downwards and properly bushed on the open end. The conduit shall be neatly arranged so that the cables enter them without bending.
- 26.7.0 **Buried cables:** The TRS or PVC sheathed cable shall not normally be buried directly in plaster. Where so specified in the special specification they may be taken in teak wood channeling of ample capacity or conduit pipe buried in the wall.
- 26.8.0 **Stripping of outer covering.** While cutting and stripping of the outer covering of the cable care shall be taken that the sharp edge of the cutting instrument does not touch the inner insulation of the conductors. The protective outer covering of the cables shall be stripped off near connecting terminal and this protective covering shall be maintained up to the close proximity of connecting terminals as far as practicable. Care shall be taken to avoid hammering on link clips with any metal instrument after the cables are laid. Where junction boxes are provided they shall be made moisture proof with a plastic compound.
- 27.0 PAINTING WORK IN GENERAL:**
- 27.1 **Paints:** paints, oils varnishes, etc, of approved make in original to the satisfaction of the Engineer-in-charge shall only be used.
- 27.2 **Preparation of surface:** The surface shall be thoroughly cleaned and dusted before painting is started. The proposed surface shall be inspected by Engineer-in-charge or his authorised agent and shall have received the approval before painting is commenced.
- 27.3 **Application :** Paint shall be applied with brush. The paint shall be spread as smooth & even as possible. Particular care shall be paid to rewets, nuts, bolts and cover lapping. Before drawing cut, it shall be continuously stirred in the smaller containers with a smooth stick while it is being applied.
- Each coat shall be allowed to dry out sufficiently before a subsequent coat is applied.
- 27.4 **Scope:** Painting on old surface in indoor situations will not include primer coat except where specially mentioned in the schedule of work or special specification. However, where rust has formed on iron and steel surfaces the spots will be painted with one anti-rust primer coat.
- 27.5 **Precautions :** All furniture fixtures. glazing floors, etc, shall be protected by covering. All stains, smears, splashings, dropping of every kind shall be removed. While painting of wiring etc. it shall be ensured that painting of wall ceiling etc. is not spoiled in any way.
- 27.6 **Painting of conduit and accessories:** After installation surface of conduit pipes, fittings switch and regulator boxes, etc. shall be painted with two coats of approved enamel paint or aluminium paint as required to match the finish of surrounding wall, trusser, etc.
28. **link clip:**
- The clip for batten wiring shall be of Aluminium conforming to I.S. specification No. 2415-1975.

APPENDIX - 'A'

Important Clauses of Indian Electricity Rules, 1956. Following clauses of

**Indian Electricity Rules, 1956 shall in particular be
taken care of in the execution of electrical works**

Clause No.	Subject
3.	Authorisation :
29.	Construction, installation, protection, operation and maintenance of electric supply lines and apparatuses.
31.	Cut-out on consumer's premises.
32.	Identification of earthed and earthed neutral conductors and position of switches and cutouts therein.
33.	Earthed terminal on consumer's premises.
34.	Handling of electric supply lines and apparatus.
41.	Distinction of circuits of different voltages.
42.	Accidental charge.
43.	Provisions applicable to protective equipment.
44.	Instructions for restoration of persons suffering from electric shock.
45.	Precautions to be adopted by consumers, owners, electrical contractors, Electrical workmen and suppliers.
46.	Periodical inspection and testing of consumer's installation.
48.	precautions against leakage before connection.
50.	Supply to consumers.
51.	Provisions applicable to medium, high voltage installations. Point of commencement of supply.
58.	Point of commencement of supply.
59.	Precautions against failure of supply; Notice of failures.
61.	Connection with earth, (low and Medium Voltage system.
64.	Use of energy at high and extra-high voltage system.
67.	Connection with earth. (High & Extra-high voltage system.
68.	General conditions as to transformation and control of energy.
All clauses under Chapter VIII on Overhead Lines.	
137.	Mode of entry.
138.	Penalty for breaking seal.
139.	Penalty for breach of rule-45.
140.	Penalty for breach of rule-82.
141.	Penalty for breach of rules.

APPENDIX-'B'

Form of Completion Certificate

I/We certify that the installation detailed below has been installed by me/us and tested and that to the best of my/our knowledge and belief, it complies with Indian Electricity Rules, 1956, as well as the C.P.W.D. General Specification for Electrical Works, 1972.

Electrical Installation at Voltage and system of supply

(1) Particulars of works :

(a) Internal Electrical Installation	No. Total Load of wiring.	Type of system
--------------------------------------	------------------------------	----------------

(i) Light point

(ii) Fan point

(iii) Plug point

(a) 3 pin 5 Amp.

(b) 3 pin 15 Amp. Others :

(b) Others :

Description

(a) Motors : (i)	HP/KW
------------------	-------

(ii)

@X1 = (iii)

(c) Other Plants:

(d) If the work involves installation of over head line/or under ground cable:

(a) (i) Type & Description of overhead line.

(ii) Total length & No.-of spans.

(iii) No. of street light & its description

(b) (i) Total length of under ground cable & its size.

(ii) No. of joint.

End joint:

Tee join:

St through joint.:

2) Earthing:

(i) Description of earthing electrode :

(ii) No. of earth electrodes :

(iii) Size of main earth lead:

3) Test Results:

(a) Insulation Resistance:

(i) Insulation resistance of the whole system
of conductors to earth.

Megohms

(ii) Insulation resistance between the
phase conductors and neutral.

Megohms

Between phase R and neutral

Megohms

Between phase Y and neutral

Megohms

Between phase B and neutral

Megohms

(iii) Insulation resistance between the phase conductors in case of polyphase supply.

Between phase R & phase Y Megohms

Between phase Y & phase B Megohms

Between phase B & phase R Megohms

(b) Polarity Test:

Polarity of non linked single pole branch switches.

(c) Earth continuity Test:

Maximum resistance-between any point in the earth continuity conductor including metal conduits & main earthing lead.

d) Earth Electrode Resistance:

Resistance of each electrode.

i) ohms

ii) ohms

iii) ohms

iv) ohms

e) Lighting Protective System :

Resistance of the whole of lighting-protective system to earth before any bonding is effected with electrode and metal in/on the structure.

ohms

Signature of Supervisor

Signature of Contractor

Name & Address

Name & Address

SPECIFICATIONS

All Specification, standard. publication etc. specified mean the latest standards. publication etc. pertaining to Electrical Installation and should conform to the following wherever applicable.

- 1) Indian Electricity Act, 1910 with its amendments.
- 2) Indian Electricity Rules, 1956 and its amendments.
- 3) Indian Electricity supply Act, 1948.
- 4) Regulation for Electrical Equipment in building by I.E.F. Landon.
- 5) The Factory Act. 1948 and its amendments.
- 6) I.S.-732-1982 Part-I, II & III code of practice for Electrical wiring and fittings in buildings for low and medium voltages.
- 7) I.S. 4064-1967 H.D. Air break switches and fuses for Voltages not exceeding 1100 volts.
- 8) I.S. 3043 - Earthing code of practice for
- 9) I.S. - 1554 Part-I - 1970 PVC insulated (Heavy duty) Electrical Cables for working voltages upto and including 110 volts.
- 10) I.S. : 694 - 1964 Part- II - PVC insulated cable with Alluminium conduits (revised) for voltages upto 110 volts.
- 11) I.S: : 5908-1970 - Electrical installations in buildings. method of measurements of.
- 12) I.S.: 4237-1967 - General requirement for switchgear and control gear for voltage not exceeding 1000 volts.
- 13) IS: 1653-1964 - Rigid steel conduits for electrical wiring (revised)
- 14) IS : 2509-1973 - Rigid steel conduits for electrical installation. (First revision).
- 15) IS: 1258-1967 - Beyonet lampholders (First revision).
- 16) IS: 418-1957 - Tungston-Filament General service electric lamps (Third revision).
- 17) IS: 374-1966 - Fans and Regulators. ceiling type, electric (second revision).
- 18) IS : 2667-1964 - Fittings. for rigid steel conduits for electrical wiring.
- 19) IS: 3419-1976 - Fitting for rigid non-metallic conduits (First revision).
- 20) National Electric Code, 1986.

ANNEXURE I.

Abstract of the Wiring Rules of the Institution of Electrical Engineer (referred to in the specification)

DEFINITIONS (See Clause 2 of the Specification)

Systems :

All electrical system in which all the conductor and apparatus are electrically connected to a common source of supply.

- 1) **Earthed:** Effectually connected to the general mass of the earth. Solidly earthed means earthed without the intervention of a fuse, switch, circuit-breaker, resistor reactor or solenoid.
- 2) **Uninsulated Conductor:** A conductor without provision, by the interposition of a dielectric or otherwise, for its insulation from earth.
- 3) **Bare:** Not covered with insulating material.
- 4) **Dielectric :** any material which offers high resistance to the passage of an electric current.
- 5) **Bunch Conductor:** When more than one conductor is contained within a single duct or groove or when they are run enclosed and not spaced apart from each other.
- 6) **Points:** In wiring as per IS : 5908-1970-Method of measurements of electrical installation in buildings
- 7) **Switch board:** An assemblage of switchgear with or without instruments, but the term does not apply to a group of local switches in a final sub-circuit where each switch has its own insulating base.

Note: In the electricity (Factories Act) special regulations, 1908 and 1944 the term "Switchboard" includes "Distribution board".

- 8) **Single pole switch:** A switch suitable for closing and or opening a circuit on one phase or pole only.
- 9) **Linked switches:** A switch the blades of which are so linked mechanically as to make or break all poles simultaneously or in a definite sequence.
- 10) **Fuse Switch:** A switch the moving part of which carries one or more fuses.
- 11) **Three Wire System:**
 - a) **Outer Conductor:** Those between which there is the greatest difference of potential. This use of the word outer must not be confused with the use of the word when applied to the external conductor of a concentric main.
 - b) **Neutral Conductors:** The term includes the neutral conductor of a 3 phase 4 wire system, the conductor of a single phase or d.c. installation which is earthed by the supply undertaking (or otherwise at the source of the supply) and the middle wire or common return conductor of a 3 wire d.c. or single phase a.c. system.
- 12) **Semi enclosed machine:** One in which the ventilating openings in the frame are covered with
 - a) Grids expanded metal or wire gauge, with openings of less than 1/4 inch so as to obstruct free ventilation.
 - b) Wire gauge, in which the openings are less than 1/41 inch but not less than 3/32 inch (diameter or width) :
 - c) Screens with smaller openings than the above.
- 13) **Totally - enclosed Machine:**

One in which the enclosing case and bearings are dust proof and which does not allow circulation of air between the inside and outside of the case.
- 14) **Pipe Ventilated Machine:** An enclosed machine in which the frame is so arranged that the ventilating air may be conveyed to it through a pipe attached to the frame, the ventilation Opening maintained by the fanning action produced by the machine - itself.
- 15) **Forced draught machine:** An enclosed machine in which the ventilating air supply is maintained by an independent fan external to the machine itself.
- 16) **Protected Machine:** One having end shield bearings and in which there is free access to the interior without opening doors removing covers.

SWITCHES. AND CIRCUIT BREAKERS

(See clause II of Specifications)

17) Switches and Circuit Breakers.:

Switches and circuit breakers (rules 2b. 36 and 37) whether' fixed separately or combined with lamps, holders or fittings, must comply with the following requirements:

- (a) Overt heading must not take place at the point of contact or elsewhere, when the full current flows continuously.
- (b) They must be so. constructed or arranged that the contacts cannot accidentally close when left open.
- (c) The basis must be of incombustible, non-conducting and moisture proof material.
- (d) Circuit breaker as must be so. arranged and placed that no combustible material is endangered by their action.
- (e) Unless placed in an engine room or in a compartment especially arranged for the purpose, they must their live parts covered. The covers must be of incombustible material and must be either non-conducting or of rigid metal and clear of all internal mechanism. For more than 6 amperes, at pressures exceeding 125 Volts metal' covers must be lined with insulating material.
- (f) In positions where they are liable to. injury or come into. contact with goods, they must be further protected by an open fronted box or other suitable guard.
- (g) Handles must be insulated and so arranged that the hand cannot touch live metal, or be injured through and adjacent fuse blowing.
- (h) Switches having a handle projecting through an open slot in the cover, must not be used.

Signature of Contractor/s

Executive Engineer

SECTION F-1A

GENERAL REQUIREMENTS

1.1 Scope of works :

The work covered by electrical specification consists supplying and installing, electrical wiring system complete in 'strict accordance with this specification and the applicable drawing and subject to. the terms and conditions pf the contract. It includes. .

- (a) Conduit a wiring system far fans, lighting paints bells, clacks sockets, etc. including fixing of lighting fixtures and fans etc. and miscellaneous paints.
- (b) Conduit and wiring system' far exhaust fans, power sockets.
- (c) Panel boards, distribution boards. switch fuse units.
- (d) Complete power and lighting cable systems. Grounding system.
- (e) Grounding system.
- (f) Conduits system.
- (g) Street lighting system.
- (h) Other miscellaneous electrical work.

1.2 Completeness of Contract:

Any work fittings accessories or apparatus which may not have been specifically mentioned in the specification but which are necessary in the equipment for efficient working of the plant should be deemed to be included in the contract and should be executed and provided by the contractors. All plant and apparatus should be complete in all the details, where such details, are mentioned in the specifications or not.

Three prints and one permanent negative of each' of the finally approved drawings incorporating all the modifications proposed by the Department should be submitted. No modifications should be made in a drawing already approved by the Engineer-in-charge without his prior consent.

Approval of the contractor's drawing will not relieve the contractor of any part of his obligation to meet all the requirements of the contract.

1.3 Guarantee :

The performance of all the equipments and the installations should be guaranteed at least for a minimum period of one year from the date of taking over the installation by the Department'. All equipments must comply with the relevant IS-BS specifications.

1.4 Interchangeability:

All corresponding parts of similar plant and equipment should be? interchangeable in every way.

1.5 Tools:

All special tools required for dismantling and assembly of the equipment covered by the contract shall be supplied as obligation under the contract.

A list of items to be supplied by the Contractor should be submitted along with the tender.

SECTION F-2A

Specifications for Electrical Installation in Buildings

1. GENERAL:

1.1 These specifications relate to the electrical installations in 'the buildings of P.W.D. Electrical. The specifications cover general requirements to be fulfilled. These general specifications are supplemented by the specifications for the particular buildings separately attached.

1.2 These specifications are governed by the General conditions of the contract attached hereto.

1.3 APPLICABLE RULES AND REGULATIONS:

1.3.1 Installation shall be carried out in conformity with the regulations for electrical equipments of buildings, published by the Institute of Electrical Engineers London (14th Edition 1966 and as amended upto date) herein after referred to as the I.E.E. wiring regulations. Where these specifications. or the special specifications for the particular building attached hereto are at variance with the I.E.E. regulations these specifications or special specifications ~s the case may be, shall be followed. The installation shall also comply with the requirements of the Indian Electricity Act, 1910 as amended up to date and rules issued hereunder and also the regulations for the Electrical Association of India. Where not specified otherwise, the installation should generally follow the Indian standard codes of practice and in their absence the relevant British Standard of practices. All the materials shall comply with the relevant Indian Standard of British Standard specifications.

1.4 DEFINITIONS:

1.4.1 The definitions of terms in the I.E.E. Regulations shall apply in general.

1.5 DRAWINGS:

1.5.1 The preliminary drawings only indicate the general scheme of requirement. The exact position of all points, control switch boxes, runs of wiring and/or conduits joint boxes, inspection boxes, mains, and sub-distribution boards, mains etc. shall be got approved by the Engineer-in-charge. All circuits shall be clearly numbered in wiring diagrams and building plans. The detailed design of a switch-board, special fixture or any other part of the electrical installation as may be called for by the engineer-in-charge shall also be supplied by the Contractor and should be got approved by the Engineer-in-charge. Three sets of completion drawings am wiring diagrams showing the installations as executed shall be supplied by the contractor alongwith the completion certificate.

1.6 MATERIALS:

All materials shall be new and of the best quality conforming to the relevant I.S.B.S. specifications. They must be the products of reliable manufacturers of many years or standings. All like parts of materials shall be interchangeable. In case pf equipments such as circuit breakers, switch fuses etc. a descriptive and illustrated literature shall accompany the tender. The names of manufacturers of various materials shall be furnished in proforma in Appendix. Samples of materials wherever required should be approved by the Engineer-in charge before use in the installation. One set of such approved samples shall be deposited with the Engineer-in-charge. All materials shall be rust-proof or rendered rust proof by application of suitable paints. The supply of all equipments, switchgears etc. 'shall be complete with accessories. fittings and mountings as may be required for their proper performance, and as specified in the relevant IS-BS Code of Practice and standards.

1.7 WORKMANSHIP:

1.7.1 Good workmanship and neat finished appearance are the prerequisites for complying with the clauses of these specifications. With a view' to ensure fine workmanship the tenderers shall employ licensed 'wiremen, with an experience of not less than 5 years in the type of work' they are engaged. The work should be done under supervisions of licensed Electrical Supervisors with good educational qualifications and considerable experience.

1.7.2 Tenderers shall furnish the names of Supervisor and their wiremen who will be engaged in this work with details of their experience.

1.8 CO-OPERATIVE WITH CIVIL AND OTHER WORKS CONTRACTORS:

1.8.1 The tenderer, after the award of the contract. shall co-operate with the civil and other contractors and shall co-ordinate his work with the work of other contractors with the least amount of dislocation and interference to the other works. Tenderers shall go through the drawings carefully and shall furnish the Engineer-in-charge with all the details of openings in the walls etc. they may be required for concealing any of the electrical equipments or accessories. Where the contractor fails to furnish such information as may be required for the purpose of concealing the equipments etc. they shall be made at his (Contractor) cost and expense. Any alteration to parts of the building shall be carried out with prior permission of the competent authority. All chaises of the structural work shall be made good at the contractor's expense and brought to the original shape finish and concur.

1.9 TESTING:

The electrical contractor shall be completely responsible for the testing and commissioning of those installations covered by these specifications in compliance with the standard procedure, in/obtaining permission of the Government Electrical Inspector. Any modification which is demanded by Government Electrical Inspector shall have to be carried out within the scope of the contract. The *contractor* shall submit four copies of drawings of installations as per regulations for shall be provided by the *contractor* for carrying out the installation work. All tests shall be carried out in the presence of the Engineer-in-charge or his authorised representative and his approval obtained for the test results.

1.10 . COMPLETION CERTIFICATE AND MAINTENANCE GUARANTEE:

1.10. 1 After the completion of the installation and testing, the contractor should furnish a certificate in the proforma In Appendix-III, at the time of taking over the installation by the Department. The installation shall be guaranteed for period of 12 months from the date of taking over by the Department. During the period of guarantee all defects in material or in workmanship shall be rectified or replaced free of cost to the Department.

1.11 TENDERER'S ABILITY:

1.11.1 In order to enable the Department to assess the ability of the tenderer to execute the work. the tenderer shall furnish evidence of his experience and capacity to carry out the work of the magnitude and nature.

1.12 RATES:

The rates of items shall include all taxes, transport, loading and unloading charge and all such charges that may be required to be incurred for the supply and installation of the materials at site. The rates shall be firm and variations in the market are not entertained. Break up figures as required in the schedule of work shall also be furnished. As far as possible indigenous materials only shall be included for supply. Where it is unavoidable, imported items may be included and tenderer should clearly indicate materials, quantity, rate and amount of these items.

1.13 STORAGE SPACE:

No covered storage space will be provided by the Department. The contractor has to make his own arrangement. However, the Department may give an open space near the place of execution where the contractor can build his own stores for executing the work.

1.14 DEPARTURE FROM SPECIFICATIONS:

The tenderer should clearly indicate departure, if any, from the specifications with reasons for the same.

1.15 EXTRA ITEMS:

Rates for extra items shall generally be derived from the rates already available in the schedule. Where it is not possible, the rates shall be mutually agreed upon and the contractor shall furnish a detailed analysis of the rates claimed by him.

2. TECHNICAL SPECIFICATION:

2.1 Supply System:

The wiring installation shall be suitable for 3 phase 4 wire. 400-440 V 50 cycles system of supply. Colour code of different phase shall be followed as per standard.

2.2 Wiring for Lights and Fans:

2.2.1 Looping system of wiring shall be adopted. No joints shall be made at intermediate runs of cables and where they are unavoidable. such joints shall be through approved mechanical connections.

2.2.2 Point wiring:

Point wiring shall consist of the branch wiring from the switch board together with the controlling switch or push as far as and including the ceiling rose or any other approved connector or socket. outlets. In case of more than one light being controlled by one switch, the wiring upto the ceiling rose of the first light including the switch shall be considered as a 'Primary point. Loop wiring from light shall be considered as a 'Secondary' point and rates shall be quoted separately, including final connections to fixtures and plugs.

Conductors:

No conductor for final sub circuit wiring for light and socket outlets. shall have across-section less than that of 2.5 sq. m (aluminium).

2.2.4 Loading:

No final sub-circuit radiating from the fuse board of a sub- distribution board and wires with 25 sq. m. (Al.) cable shall carry more than 10 lights, fans or socket outlets or a connected load of 800 watts whichever is greater. The {allowing wattages may be assumed for estimating the load on each sub-circuit unless otherwise known as specified.

Incandescent Lampts	1 00 watts
Ceiling fans	60 watts
5-A Socket Outlets (lighting)	100 watts
4. ft. fluorescent tube.	50 watts

5 ft. fluorescent tubes.

100 watts

In each sub-distribution board at least one way preferably two ways shall be left spare for future requirement. A wiring diagram giving the details of the exact utilization of the ways shall be prepared and fixed in the sub distribution board itself or any other easily accessible place. The ways of sub-distribution boards shall be accordingly numbered.

2.2.5 Local Control Switches (General) :

Local control switches for circuit carrying not less than 5-5 shall be piano type and shall conform to relevant I.S. Standards. The switch shall be 'ON' when the knob is in the down position. All local control switches shall be connected in the phase or live conductor only and not in the neutral conductor, switches shall be fixed in iron clad box and shall be so placed that the centre of the switch box is 1.3 mtr. from the finished floor level unless otherwise stated. All switch boxes shall be provided with 1/8" thick Perspex cover fixed to the switch box with chromium plated counter sunk screws (brass).

2.2.5A Switches (Two way) :

(a) Two way switches shall be piano type single pole, (double throw, 250V, suitable. for flush mounting and of 5A capacity as per the drawings. All switches shall be recessed in an embedded metal box.

(b) Each box shall have suitable outlet for fixing conducts directly.

(c) Each box shall have Perspex cover painted inside with the wall colour, if required.

(d) Each switch shall be suitable for the position in a corridor stairway wiring.

2.2.5B Switch Boxes (General):

Electrical circuits shall be written suitably on the cover of all switch boxes. as approved by the Engineer-in-charge (Elect) whenever different phase are terminated in a switch box bakelite partition shall be provided. Each case shall be provided with a G.I. Earth stud nut and washers for earth connectors.

2.2.6 Ceiling Rose:

Ceiling rose shall be used on circuits having a voltage normally exceeding 200V. Only one flexible cord shall be attached to a ceiling rose. Only 3-pin 5A socket outlet shall be provided in lighting circuits. All socket outlets shall be provided with a control switch and they shall be mounted in switch boxes in an approved manner.

2.2.7 Fittings:

These shall be of approved type as specified in the tender schedule. The sub circuits leads should terminate in a ceiling rose or conductor in the fitting and internal connection made there from. Wherever these fitting are suspended they shall be done so through the conduits and ball and socket joints. All fittings shall be grounded by a G.I. conductor not less than 16 S.W.G.

2.2.8 Flexible wiring:

Flexible cords of not less than 23/0076 size shall be used. The weight of suspension shall be governed by I.EE. Regulations.

2.2.9 Ceiling Fans:

All ceiling fans shall be wired to ceiling rose and suspended from a hook shackle or clamp and insulated from the same. All joints in the suspension road shall be screwed and secured. by means of split pins. The fan clamps supplied by the Contractor shall be suitable for the ceiling or roof member as the case may be. For concrete roofs, fan hooks shall be buried in concrete during construction in an approved manner and securely bound to the reinforcement.

2.2.10 Conduits and Earthing:

All conduits feeding lighting and fan circuits shall be provided with earth continuity G.I. conductor as specified for power wiring. All conduits shall be as specified for power wiring.

2.3.1 Point wiring:

Point wiring for power shall be as defined under section 2.2.2 and shall include the switches and sockets.

2.3.2 Loading:

All distribution board for power wiring shall be not less than 15A per way. Loading per way shall not exceed' normally 100 watts. The following loads may be assumed if exact figures are not known.

3-Pin 15A Outlets	1,000	Watts
3-Pin 5A Outlets	100	Watts

2.3.3 Wiring for Motors:

2.3.3.1. Final sub-circuits loop in motors shall be connected to separate ways of the Distribution board even if the current in the sub-circuit is less then 15A. No looping is permissible.

2.3.3.2 All wiring shall be carried in H.G. conduit as specified in I.S. specification for gauge for different sizes of conduits.

When the motor is resiliently mounted flexible conduit with approved adopters shall be used for the last few feet. Where cables are used sufficient loop shall be left.

2.3.3.3 All switch fuse units controlling circuits feeding motor shall be provided with H.R.C. fuses or as specified.

2.3.3.4 The frame of every motor and its association control gear shall be earthed by two separate and distinct connections to earth connector shall be capable of carrying 3 times the rating of fuse or 1.1/2 time the setting or the circuit breakers but in no case less than No.8 S.W.G. or 7064" or equivalent cross section of copper. Where practicable, the earth connections shall be visible for periodical inspection. Gas or water pipes shall not be used for earth connections.

2.3.3.5 Socket Outlets and Control Switches 5A and 15A :

All socket outlets shall be of 3 pin type, the third pin being connected to the earth stud of nearest distribution board by separate earthing wire. The socket shall conform to I.S. : 1293/1938, single pole, piano type. Each socket outlets shall be provided with a control switch of appropriate rating and as specified. The switch and socket shall be mounted inside the iron clad box provided with 1/8" Perspex cover as directed by the Engineer-in-charge or as specified in schedule .of quantities. Inside switch box ample space shall be available around switches for connecting wires to switches. All socket outlets for power shall be mounted at the skirting level unless otherwise specified or as directed by the Engineer-in-charge.

The three phase plug receptacles shall have their earth terminals connected by independent earth wires to ring main earth strips on the building. In buildings where explosion proof fixtures are installed single phase plug receptacles as well as light points shall be connected to ring main ground bus installed in the building by separate earth wires of approved size."

Socket outlet shall have some provision not to receive the matching plug unless the grounding pin is in correct position. The grounding pin of the plug shall make the contact first and break the contact last at the time of . inserting or removing the plug respectively.

The grounding terminal shall be connected to the enclosed metal body by providing G.I. stud. nut washers welded to the box.

Each unit shall be suitable for flush mounting as required and indicated in the applicable drawings.

Combination unit of socket outlet and switch shall be complete with necessary internal wiring. The witch/socket shall be mounted on M.S. bracket enclosed in a box.

2.4 Conduit Wiring:

2.4.1 Where conduit wiring is adopted the type and size of the conduit shall be as indicated in the drawing. The minimum of the conduit shall be 19 mm.

2.4.2 The contractor shall thoroughly study the' structural arrangements of the buildings and wherever, necessary shall in consultation with Department's representatives at site, make suitable adjustments in the cable routings, earthing arrangements, and location boxes, fitting etc. with a view to avoid interference with any part of the building, structure, equipment or any other work in the building or to effect any improvement in the arrangement.

2.4.3 Protection of conduit against rust:

Conduit shall be given two coats of oxide paint before they are placed in position. All exposed conduit shall be planted after installation with the colour as approved by the Engineer-in- charge. This do not apply to galvanised conduit.

2.4.3.A Protection against insects and damp:

In order to minimise cocensation or sweating inside the conduit, system shall be properly drained any ventilated in such a manner as to prevent the entry of insects.

2.4.4 Conduit shall first be installed as a complete system without cables and shall be continuous from outlet to outlet from fitting to fitting and mechanically and electrically connected to all boxes and fittings.

2.5 SPECIFICATION FOR POWER CONTROL AND TELEPHONE CABLES :

1. SCOPE:

- i. The specifications cover the supply and installation of meduim voltage power and control cables either in ground or trench depending on the conditions at site including accessories for the same. The work in general, consists of supplying, laying, jointing terminating and connecting all. 1.1. KV APLSTS PVC power and control cables.
- ii. The contractor shall supply all accessories including jointing and terminating materials, compound, tapes supporting materials, cleats cables lugs, concrete stabs, bricks sand, cable markers etc, as required to make the installation work including digging and back filling of the trenches as required.

II. SPECIFICATION:

- i. All power cables to be supplied mentioned as 'APLSTS' in the Schedule should be mass impregnated, non draining, paper insulated lead sheathed. double steel tape armoured and must comply with the latest ISI BS specifications.
- ii. All cabling materials such as cable compound, cable lugs, tapes shall be of approved quality acceptable to the type recommended by the manufacturer of the cable for which it is used and

- approved by the Department.
- iii. Installation of all equipment shall also conform to the applicable. Codes and practice as per the IS and shall be executed to comply with the latest Indian Electricity rules as regards the safety, earthing of equipments and other essential provisions specified therein.
- iv. Only approved make of cable shall be used. ICC and CCI will be preferred.
- v. The cables shall generally be laid as per is Code of practice.

III. **GENERAL RULES CABLE LAYING:**

- i. Installation shall be carried out in a neat, workmen like manner by skilled experienced and competent workmen in accordance with the standard practices.
- ii. Cables shall be laid preferably in one piece length to avoid joins. If straight joints are found necessary, these can be introduced with prior approval of the Engineer-in-charge. The cost of the straight joint however, shall not be borne by the Department. But in no case joint shall be within the conduit G.I. pipe and duct.
- iii. Proper care should be exercised in handling the cable to avoid formation of kink etc. and should it become necessary a cable be bent to a radius not less than 20 times the overall diameter of the cable.
- iv. Method of installation, routing of cable etc. shall in every case be subject to the Department's approval and the contractor shall modify and or certify at no extra cost to the Department any portions of the installation which do not meet with the Department's approval. All damages to the civil and other works on this account shall be made good by the contractor at no extra cost to the Department.
The electrical contractor while notifying the building contractor for such work shall furnish the proper drawings, fully explaining the work involved or indicate at site actual work to be carried out as may be required by the building contractor. The electrical work of any such work as soon as the, electrical work with respect to the same has been completed.
- v. Where cables pass through hume pipes, contractor shall fix hard wood bushed round the cables at the ends of hume pipes. Where the cables pass through the floors or chambers and in such other situations as the Engineer shall require, the contractor shall seal cable holes in a manner approved by Engineer-in-charge. Where cable pass through roads nallahs, etc. cables must be protected by Class 'A' Hume pipe of diameter not less than 6" (15cms.)
- vi. The cable route shall be the shortest and there shall be minimum interference with built up areas, lawns etc.
- vii. Care shall be exercised for providing suitable props for supporting other service lines on earth at the time of excavation. Where cutting of a lawn become inevitable it should be with the approval of the Engineer-in-charge.
- viii. Excavation of the trenches shall be executed with vertical sides and the trenches shall be kept as straight as possible. The exact location of each trench shall be served by the Engineer-in-charge. On the site when the contract is in a position to commence each portion of the work.
The trench shall be not less than 1/2 meter wide and 90 cms deep. If more cables are to be laid, the width should be suitably increased.
- ix. After the cables are laid, the trench shall be filled in layers, the earth in each layer being well rammed by spraying water and consolidated and sufficient allowance made for settlement. The extra earth over the trench should be removed from the place of trench to a place as decided by the Engineer-in-charge at site.
- x. Ends of cables shall be properly sealed to prevent entry of moisture prior to installation.
- xi. Where it is as specified as 1/2 core cables the 1/2 core shall be a neutral conductor having reduced section.
- xii. For all multicore cables each core and tails shall be brought out, marked and or coloured in an approved manner.
- xiii. Cables termination shall be done with suitable compression brass glands in the case of PVC cables and cast iron trituration boxes in the case of APLSTS cables. The armour should be connected to the, right main earth in building with duplicate earth wires as per the relevant IS/BS specification.
The core insulation over each conductor shall however be retained through out the run of the conductor upto the end where lugs shall be fitted thereon for connections. The lugs shall be fitted by means of approved < solder and flux such as a lead, and Eyrer NO.7 liberally used. The joint shall be mechanically strong and pressure tested.

2.6 **DISTRIBUTION BOARDS AND PANELS:**

General Requirements:

- 2.62 All distribution panels shall comply with I.E.E. Rules 60- 61. A clear distance of 0.91 m metre in front of the switch board shall be kept. Where bare connections or attachments are provided at the back of the 'Switch board the space behind the panel shall be either less than 0.299 meter or more than 0.762 main width there

shall be a passage way from the further outstanding part of any attachment or conductor. If the space behind the switch board exceeds 0.70 m width there shall be a passage way from either end of the switch board clear to height of 1.928 m width 0.299 m. All wiring connection shall be made neatly and securely.

- 2.6.2 For circuits carrying more than 10 Amps. tinned cable sockets shall be used. All connections shall be so made as to form their own diagram. Circuit shall be clearly numbered to correspond to 1 wiring diagram. Names of the distribution boards shall be painted as directed by the Engineer-in-charge. All the switch fuse units and isolators D.Bs. shall be complete with earthing studs lugs neutral bar link, H.R.C. fuses and of approved make.
- 2.6.3 Skeleton type panels shall have a rigid form work adequately braced and supported. The switch and distribution boards shall be neatly arranged in the frame. The details of the frame work and the arrangement of switches shall be got approved by the Engineer-in-charge before the panel is fabricated:
- 2.6.4 All cubical type panels shall have rigid supporting frames adequately braced over which sheet metal shall be neatly secured. All switches, distribution boards etc. shall be neatly arranged on the panels and all connections made from the back of switches. The panels shall be rendered dust and vermin-proof. The interior of the panels shall not be accessible to unauthorised persons.
- 2.6.5 The recess type boards shall be embedded in wall in a cupboard with a metal hinged door with locking arrangement. In all recessed conduit work all distribution boards shall be recessed. Where recessing is not possible, free standing panel may be provided as approved by the Engineer-in-charge.
- 2.6.6 All individual components i.e. switch fuse units D.Bs. etc. shall be connected by earth continuity wire of appropriate size with the main earth bus of the panel D.H. etc. The panel switches or D.Bs. shall be earthed by the less than 2 distinctive paths to earth. Earthing of metallic parts of exposed metal shall not be effected through any structural metal work which houses the installation. Where metallic parts are not required to be earthed and are liable to become alive should the installation of the contractor become defective such metallic parts shall be separated by durable non-conducting material from any structural work.
- (a) Power panels shall be 3 phase, 4 Wire, 400/230 volts for the distribution of 3 phase .01' single phase power loads. Lighting panels shall be 3 phase 4 wire 400/230 volts for single phase lighting load distribution on all 3 phase.
 - (b) All panels shall be done or protected front type with no mechanical or electrical defects. (c) . Bus bars shall be of electrolytic copper or aluminium as specified and the properly tinned sizes as indicated on applicable drawings as required.
 - (d) AU knock outs for branch circuits, conduit entries shall be drilled in and filled as required. For lighting panels the top and bottom cover plates shall be removable type.
 - (e) Main disconnect device for all panel boards shall be of switches of disconnect type and of the size as indicated shall be mounted directly below the panel or through a short thread conduit of required size.
 - (f) The main disconnect for all panel boards shall have an entry suitable for PVC armoured cable from bottom.
 - (g) All panel boards shall be provided with an earthing terminal and lug for connection to the grounding system.
 - (h) Temperature rise of all electrical parts shall not be more than 3000 with full load amperes at room temperature. Buses shall be securely supported so that ordinary vibrations will not cause any of the parts to become loose.
 - (i) All barriers and supports of current carrying parts shall be of moisture resistant insulating material and shall not be adversely affected by arcing.
 - (j) The locations of panels shown in the drawings are only tentative. Panels may be located at a place approved by the Engineer-in-charge.
 - (k) All civil works connected with fixing such as grouting chasing and making good shall be the tenderer's responsibility.
 - (m) Wires adequate capacity with proper size of lugs shall be used for inter connections.
 - (n) Panel should be self supported on angle channel iron frame work. It should be preferably of bolted construction in case of transportation and flexibility. The frames shall be of the required size for the mounting of the equipment on it. It shall be bolted or grouted rigidly after leveling and alignment.
 - (o) The cupboard and D.B. should be of such size so to be accommodated in the existing room as per I.S. rules and I.S. codes of practice for installations of medium voltage switch gear.
 - (p) Fabrication drawing showing the detailed dimensions and panels and its components indicating the frame work, earthing positioning of switches, D.Bs. cable boxes, adopter chambers etc. shall be furnished to the Engineer-in-charge for his approval. All material to be got approved by the Engineer-

in-charge. Panel should be guaranteed for satisfactory operations for a period of one year after handing over.

- (q) The panel should be painted with anticorrosive paint suitable for humid and salty atmosphere on two coats of primer.

Switch Gears, Powers Panels D.B. and S.F. Us.

- 2.6.8 The main busbar shall have continuous current rating as specified with neutral bar having half of full load rating of the phase busbar. The sizes of the bus bars shall be so selected that the current density in bar does not exceed 150 amps. per sq.m. for copper. The length of bus-bar chamber should be as suitable length to fix all the switches etc. as per the prevailing standards, clear spacing of two adjacent buses shall be 1 1/2" minimum bar should be lapped all along with colour coated 11 KV grade PVC tape. The maximum internal of support for each unsupported length shall exceed 600 mm.

The bus bar shall be of copper/ aluminium and fabricated to the relevant standards specification. In case aluminium bus bar is used special with high conductivity aluminium bus bar alloy E 91 C frame conforming to E.S.S. 2898 shall be used. The current density shall not exceed 800A per sq. inch. Hylam barners will be provided over the joints to prevent any short circuit.

The bus enclosures shall be made out not less than 16 gauge M.S. sheet construct on with angle iron support. All interconnections between bus bars S.F. Us. and D. Bs. shall be of adequate size and details of such inter connection shall be furnished to the Engineer-in-charge for his approval.

The bus bar shall be air insulated extensible type rectangular one. The bus bars chamber shall be dust tight by providing gaskets secured properly so as to tender it vermin proof.

The Combination Fuse-switch unit should comply with IS 4064 BS 861 and BBS 2510 wherever applicable. It should be suitable to accommodate High Rupturing Capacity Cartridge Fuse links complying with IS 2208 or BS 88 and having a certified rupturing capacity of not less than 35 MVA at 440 volts (AC5 duly). The switch gear (panes. D. Bs. etc.) shall be installed generally as per IS-Part- I 3072 and as specified and shown in drawings.

All fuse switch units shall be provided with non-deteriorating HRC fuse links complying with IS 2208-1962 and having rupturing capacity of 35 MVA at 415 volts. or as specified.

All switches above 60 amps. rating shall be provided with suitable size adapted boxes. All switches mounted on the top of the busbars shall be provided with detachable type reverse entry adapter boxes. Suitably engraved labels shall be provided for each circuit as well as for the board.

A meters sector switches and LMH metre shall be provided where specifically mentioned. Small wiring for the inter-connecting shall be colour coded and provided with numbered fuses for easy identification of circuits.

- (a) The distribution boards should be totally enclosed metal clad complying with B. S. 214. The M. S. sheet steel enclosures for recessed D. Bs. shall be of not less than 14 gauge.
- (b) The D. B. shall be with hinged door and the locking arrangements as approved by the Engineer-in-charge.
- (c) All the components shall be enclosed in the enclosure. The mounting of D. B. shall be got approved by the Engineer-in-charge before carrying out the installation.
- (d) The D. Bs. shall have proper size cut outs for conduits entry or cable entry as required and these shall be made on site.
- (e) Adequate spacing shall be provided inside the D. Bs. for easy removal of the fuses and carry out the inter connection:
- (f) A set of insulating barriers have to be provided between incoming breakers switches and fuses.

Switch fuse Units:

- (a) All the D.P. T.P. and TP.N. switch fuse units shall be totally enclosed iron clad quick make, quick break type to best Indian make conforming to the I.S. or B.S. 3185 specifications. All the switch fuse units shall have mechanical interlock with a door, so that the door cannot be opened when the switches are in 'ON' position. The switches should be of double break solution type to ensure safety.
- (b) Each TP. & TP.N. switch fuse unit shall be earthed with two distinct earth connections.
- (c) Suitable insulator shall be provided. between phase.
- (d) There shall be suitable neutral link in the fuse box.
- (e) All T. P. & T.P.N. switch fuse units shall be rated for 500 volts and D. P. (required for single phase supply) and S.P.N. switches for 250 volts.
- (f) The H.R.C. cartridge fuse shall conform to H.S. 88 (1952).

The O.C.Bs. ACB shall be suitable for 400/440 volts 3 phase 50 cycle supply capable of interrupting a fault MVA of not less than 31. The circuit breaker shall conform to the BSS-

936-1940 BSS 3659 with such tripping arrangement as may as required under special specifications for the building. Efficient and foolproof mechanical interlocking shall be provided for the safe operation and maintenance. The rate shall be inclusive of the first filling of oil.

2.7 Instrumentation :

The instruments and meters wherever necessary shall be housed in special sheet steel box located between switch fuses units and bus bar chambers. The instruments etc. shall be mounted on the hinged cover with their dial flushed. All instruments shall have protective H. R. C. fuse links. All interconnections and small wiring shall be neatly dressed arranged and duly coloured for easy identification of circuits.

Meters shall be provided as required in the Schedule, Meters shall be dead head and be suitable for 400/440 volt 3 phase 4 wire 50 cycle (in balanced load) supply.

Each selector switch shall be 3 point and of minimum 250 volts grade with silver tipped contacts suitable for metering circuits, current transformers shall be of 5VA burden and commercial metering accuracy. indicating lamps shall be panel mounting type preferably of 250V grade. Every unit shall be rewired and interconnected to the system for its required Indicating performance. Indicating lamps shall have independent circuit fuse.

2.8 FIXING OF LIGHTING FIXTURES:

1. Location of fixtures their manner of fixing mounting height etc. are indicated in relevant drawing. Actual location and levels shall however be arrived at site in co-ordination with other service etc and prior approval of the Engineer-in-charge regarding the actual location. Manner of fixing shall be obtained before the work is taken up in hand.
2. In all cases the contractor shall provide necessary interconnection wiring earthing painting etc. all necessary for complete installation. The contractor shall also test and commission the fixtures during completion of the work.
3. General arrangement of fixtures layout is indicated in drawings. Care shall be taken to see that all light fixtures are in a row in a room or particular area, are in absolute line and plumb and are symmetrically disposed with respect to finished surfaces of walls columns beams etc. .
4. The inter-connections wiring from the light outlet point up to the fixture shall be carried out by means of flexible copper wire of 'section not less than 1.5 mm²’.
5. All fixtures suspended by means of conduits shall be done with all and socket joints or as per approved design.

2.9 Telephone System:

1. Empty conduits shall be done, recessed or exposed to surface along with pull boxes, junction boxes and telephone outlet boxes, in areas and location' as indicated in the relevant drawing as per materials and methods as described in regard to conduits under section "Wiring in Conduits" except the G.I. pull wires of gauge not less than 20 SWG shall be kept pulled through conduits in all sections so that in future telephone wires can be pulled easily.
1. Location shown on the drawing are approximate and final location shall be decided in the field by the Engineer-in-charge.

SECTION G

SPECIFICATION FOR EARTHING.

1. Installation of Earthing Plates :

All installation of earthing shall conform to Indian Electricity Rules, 18.3043 latest edition and IEE. The copper earth plates should be tinned before installation. The earth plates of copper 60 cm x 60 cm x 3.515 mm thick size as mentioned in the schedule be in separate pits at least 150 cms to 300 cms. away from the building at a depth necessary to reach moist earth surface but with a minimum depth of 2.5 mtr from the finished ground level upto the top vertical edge of earth electrode. The earth plate shall be thoroughly cleaned to remove all dirt from the surface and be tinned properly for electrical contact with the main ground. Each earth pit should be provided with 38 mm. dia G.I. pipe 2.5 Mts. long or more depending upto the depth of pit, put over the vertical edge of earth plate (with top end of pipe provided with a closed coupler). Alternative layers of salt and coke shall be provided surrounding the plate. The pits shall be filled when the plates are in position and with the approval of Engineer-in-charge.

To facilitate watering the pit, a concrete compartment should be made with funnel with mesh and cover plate as per rules provided in ISI regulation. The masonry enclosure shall be 25 cm x 25 cm x 25 cm (deep) with C.I. lid of 23 cm x 30 cms size. After installation, the earthing resistance of each earth plate should be measured by resistance meggar in the presence of Engineer-in-charge, three days after the completion of earthing work, and the value should conform to regulations.

Signature of Contractor/s

Executive Engineer

Division.

*****0%0%0%0%*****0%0%0%0%*****